



# Avid® Media Composer v3.5.1

## ReadMe

---

### Revision History

Date Revised	Changes Made
April 27, 2009	At this time, Avid does not recommend updating to the x.5.1 version of the editor if you are working with MPEG50. You might experience problems when editing in trim mode.
April 13, 2009	Added to the Compatibility and Installation sections of “ <a href="#">Limitations and Known Issues</a> ” on page 24. Created document with bug numbers turned on for tracking purposes.
March 24, 2009	Added to “ <a href="#">Fixed in Avid Media Composer v3.5.1</a> ” on page 4.

**IMPORTANT: Avid periodically makes software updates and Customer Patch Releases (CPR) available for download on Avid.com at the following location:**

[www.avid.com/support/downloadcenter/index.asp](http://www.avid.com/support/downloadcenter/index.asp)

**Please check the above site regularly for information on available downloads for your product.**

### Important Information

Avid® recommends that you read all the information in this ReadMe file thoroughly before installing or using any new software release.

**Important:** Search the Avid Knowledge Base for the most up-to-date ReadMe file, which contains the latest information that might have become available after the documentation was published.

This document describes compatibility issues with previous releases, hardware and software requirements, software installation instructions, and summary information on system and memory requirements. This document also lists hardware and software limitations.

---




# Contents

Symbols and Conventions.....	2
If You Need Help .....	3
Fixed in Avid Media Composer v3.5.1.....	4
Compatibility Chart .....	5
Setting up the NVIDIA Card .....	10
Shared Storage Support.....	12
Before You Install the Editing Application.....	12
Installing the Software .....	17
New in Avid Media Composer v3.5 .....	18
Fixed in Avid Media Composer v3.5 .....	23
Limitations and Known Issues .....	24
Extending Your Usable Address Space and Adding RAM for Improved Performance (Windows) ..	61

# Symbols and Conventions

ReadMe documents use the following symbols and conventions:

---

Symbol or Convention	Meaning or Action
	A note provides important related information, reminders, recommendations, and strong suggestions.
	A caution means that a specific action you take could cause harm to your computer or cause you to lose data.
	A warning describes an action that could cause you physical harm. Follow the guidelines in this document or on the unit itself when handling electrical equipment.

Symbol or Convention	Meaning or Action
>	This symbol indicates menu commands (and subcommands) in the order you select them. For example, File > Import means to open the File menu and then select the Import command.
▶	This symbol indicates a single-step procedure. Multiple arrows in a list indicate that you perform one of the actions listed.
<i>Italic font</i>	Italic font is used to emphasize certain words and to indicate variables.
Courier Bold font	Courier Bold font identifies text that you type.
Ctrl+key or mouse action k+key or mouse action	Press and hold the first key while you press the last key or perform the mouse action. For example, k+Option+C or Ctrl+drag.

## If You Need Help

If you are having trouble using your Avid product:

1. Retry the action, carefully following the instructions given for that task in this guide. It is especially important to check each step of your workflow.
2. Check this ReadMe file for the latest information that might have become available after the documentation was published. Also check online for the most up-to-date ReadMe because the online version is updated whenever new information becomes available. To view the online ReadMe, select ReadMe from the Help menu, or visit the Knowledge Base at <http://www.avid.com/readme>.
3. Check the documentation that came with your Avid application or your hardware for maintenance or hardware-related issues. In addition to the printed documentation supplied with your editing application, the documentation is supplied in PDF format when you install the application. Topics that you print from the Help have limited page layout and formatting features. If you want to print a higher quality version of Help information, Avid recommends that you print all or part of the PDF version of the appropriate Avid manual included in the Online Library for your editing application. To access the Online Library, select Help > Online Library from within your Avid editing application.
4. Visit Avid Online Support at [www.avid.com/onlineSupport/](http://www.avid.com/onlineSupport/). Online support is available 24 hours per day, 7 days per week. Search the Knowledge Base to find answers, to view error messages, to access troubleshooting tips, to download updates, and to read or join online message-board discussions.

# Hardware and Software Requirements

To access the list of qualified and supported platforms:

1. Go to [www.avid.com/products/](http://www.avid.com/products/)
2. Choose your product.
3. Click System Requirements.

## Fixed in Avid Media Composer v3.5.1

The following have been fixed:

- **Bug Number:** UDevC00122261. (Macintosh only) Permission errors prohibiting multiple users to log into the Avid editing system. This has been fixed, however, you need to remove any pre-existing AMA Logger files before you start the Avid editor.

To remove any pre-existing AMA Logger files:

1. Before you start the new Avid editor application (v3.5.1), go to Macintosh HD/Users/Shared/Avid *product name*/Avid FatalErrorReports.
2. Delete all AMA Loggerxx\_xx\_xx.log files. (The logger files display a created date, for example: AMA Logger03\_11\_09.log.)

This removes the old logger file from the previous version of the Avid editor (v3.5). A new logger file gets created when you log into the Avid editing application (v3.5.1), this logger file does not have any permission errors prohibiting multiple users from logging in.

3. You should be able to start the Avid editor application as multiple users.
- **Bug Number:** UDevC00120187. Previously, you might have experienced extremely slow timeline response time when working with XDCAM HD and XDCAM Proxy media in an Avid Unity MediaNetwork or Avid Unity ISIS shared storage environment. This has been improved. You should delete the MCState file and delete your Project Setting to take advantage of this new fix.
  - **Bug Number:** UDevC00122023. Previously, some DV50 QuickTime imports did not import audio. This has been fixed.
  - **Bug Number:** UDevC00121900. Previously, dragging a Color Correction template from a bin to a bucket did not apply the settings to the bucket. This has been fixed.

## Compatibility Chart

The following table lists the operating system, NVIDIA® driver, QuickTime®, Windows Media™, Avid Interplay®, shared storage, Sony® XDCAM™, Panasonic® P2, and Pro Tools LE® versions that were qualified with the Avid editing applications. Also listed are the third-party applications such as Boris Continuum Complete, Avid DVD by Sonic™, Sorenson Squeeze®, and SmartSound® that ship with the editing applications.

Item	Versions	Comments
Microsoft® Windows® OS Support	Windows XP Professional with SP2 or SP3  Windows Vista® Business 64 with SP1  Windows Vista Business 32 with SP1  Windows Vista Ultimate 64 with SP1	Windows Vista Business 32 is supported on Avid Media Composer® software only, and Avid Media Composer with Adrenaline, Mojo SDI, Nitris DX or Mojo DX.  Windows Vista Business 32 is supported on the HP® xw4600 systems with Avid Media Composer with Mojo DX (no DNxHD capture.)  Windows Vista Business 32 is also supported on the HP 8510w, HP 8710w and Dell® 6300 laptops with Avid Media Composer software only.
Macintosh® OS Support	Leopard® v10.5.5 and v10.5.6	The Leopard OS has been qualified with the Mojo, Mojo SDI, Adrenaline, Mojo DX and Nitris DX hardware.
QuickTime Support	v7.5.5 and v7.6	QuickTime v7.6 has been qualified with Leopard v10.5.6. It was not qualified with v10.5.5.
Windows Media Version Support	Windows Media Player 11	If you do not have Windows Media Player 11, access the download at <a href="http://www.microsoft.com">www.microsoft.com</a> .  Windows Media export compatibility is subject to Microsoft Windows Media updates.

Item	Versions	Comments
Avid Interplay Support	See the <i>Avid Interplay ReadMe</i> for supported versions.	Macintosh editing applications are not supported in an Avid Interplay environment. <b>IMPORTANT: The Avid Interplay components that get installed on the editing application must be updated to the Avid Interplay version that is released with the editing application. These include the Media Indexer, Interplay Access, Interplay Framework, Interplay Transfer Client and ProEncode Client. The Avid Interplay Server components can remain on the previous releases listed as supported. For details, see the “Avid Editing Application Compatibility with Interplay Releases” topic in the Avid Interplay ReadMe.</b>
NVIDIA Driver Support	169.47 (This is the version of driver tested with our editing applications. DO NOT upgrade to any other version.)	See <a href="#">“Setting up the NVIDIA Card” on page 10.</a>
Shared Storage Support	Avid Unity™ MediaNetwork and Avid Unity ISIS®.	See <a href="#">“Shared Storage Support” on page 12.</a>

Item	Versions	Comments
Pro Tools	Pro Tools LE v7.3.1 and v7.4.x Pro Tools LE v8.0cs1 and higher. Pro Tools HD v8.0cs1 and higher.	<ul style="list-style-type: none"> <li>• For information on supported versions of Pro Tools in an Interplay environment, see the <i>Avid Interplay ReadMe</i>.</li> <li>• Interoperability is supported with Pro Tools LE v7.3.1 and v7.4.x; Co-install is not supported with these versions.</li> <li>• With Pro Tools HD v8.0cs1, Media Composer (Windows only) supports the Video Satellite feature. For more information, see the <i>Video Satellite Guide</i> provided by Digidesign®.</li> <li>• With Pro Tools LE v8.0, and HD v8.0 and higher, co-installation of Media Composer (Windows and Macintosh) and Pro Tools is supported. See also <a href="#">“Co-Install Notes for Avid Media Composer and Pro Tools” on page 8</a>.</li> </ul>
Sony XDCAM driver	PDZ v2.23 and FAM v2.04 (Windows XP and Vista 32)  v2.8.1 (XDCAM Transfer for Macintosh)	<p>Avid supports the Windows XP and Vista 32 device driver for XDCAM decks, the Vista 64 device driver is not available at this time.</p> <p>Avid recommends you install the Pro Disc 2.04 driver on the Windows XP system running SP3 when using the following Sony PDW devices: PDW 1500, PDW HD1500, PDW 700, PDW 350, PDW F75, PDW F70, PDW D1. The driver can be downloaded from Sony's website <a href="http://esupport.sony.com/">http://esupport.sony.com/</a>.</p> <p>Avid recommends you install the VFAM driver v2.1.0 when using the PDWU1 device. The driver can be downloaded from Sony's website <a href="http://esupport.sony.com/">http://esupport.sony.com/</a>.</p>

Item	Versions	Comments
Panasonic P2 driver	(Windows XP and Vista) Driver version for P2 devices: v2.02 - v2.4  (Macintosh) Driver version for P2 devices: v1.2	There is currently no P2 writeback support for Macintosh clients.
Boris Continuum Complete	v5.0.4	Ships with: Avid Media Composer Avid NewsCutter® Avid Symphony™ Nitris® Avid Symphony Nitris DX
Avid DVD by Sonic	v6.1	Ships with: Avid Media Composer Avid NewsCutter Avid Symphony Nitris Avid Symphony Nitris DX
Sorenson Squeeze	v5.0	Ships with: Avid Media Composer Avid NewsCutter Avid Symphony Nitris Avid Symphony Nitris DX Sorenson Squeeze is not compatible with systems running Vista 64.
SmartSound	v4.5	Ships with: Avid Media Composer Avid NewsCutter Avid Symphony Nitris Avid Symphony Nitris DX SmartSound is not compatible with systems running Vista 64.

## Co-Install Notes for Avid Media Composer and Pro Tools

When you co-install Avid Media Composer and Pro Tools note the following:

- Co-install does not support both applications launched simultaneously.
- Co-install of Pro Tools LE with Mbox 2 Pro is not supported with Mojo, Mojo SDI or Adrenaline due to Firewire conflicts.

- Co-install was not qualified with Windows Vista 64.
- Install Pro Tools first and then Media Composer.
- When you uninstall Pro Tools, choose to uninstall just the application not the audio drivers. On a Macintosh Pro Tools system, this is named the “Safe Uninstall.”
- Media Composer was tested with the Mbox and Mbox 2 as valid I/O peripherals. If you uninstall the audio drivers for these devices, Media Composer will no longer see the Mbox or Mbox 2.
- If you run into any issues, uninstall both applications and reinstall Pro Tools first, then Media Composer.

## Co-Install Supported Configurations

The following table provides the list of supported Avid Media Composer v3.5 products with the Pro Tools v8.0 peripherals. An X indicates the co-install is supported. Only Mbox and Mbox 2 are approved as valid I/O peripherals.

<b>Pro Tools</b>	<b>MC Software Only</b>	<b>MC with Mojo SDI</b>	<b>MC with Mojo</b>	<b>MC with Adrenaline</b>	<b>MC with Nitris DX</b>	<b>Mojo DX</b>
Mbox 2 Pro (FW)	X	Not Supported	Not Supported	Not Supported	X	X
Mbox 2	X	X	X	X	X	X
Mbox	X	X	X	X	Not Tested	Not Tested
Mbox Mini	X	X	X	X	X	X
Mbox Micro	X	X	X	Not Tested	Not Tested	X
Digi 003 (FW) <sup>a</sup>	X	X	X	X	X	X
Digi 002 (FW) <sup>a</sup>	X	X	X	X	X	X
Pro Tools HD (in CPU)	X	X	X	X	X	X
Pro Tools HD (w/Chassis)	Not Tested	Not Tested	Not Tested	Not Tested	Not Tested	Not Tested

a. Applies to 002 and 003 Rack and Console units, and 003 Rack +. When used with Mojo, Mojo SDI, or Adrenaline, connect the 002 or 003 to an approved Firewire HBA card.

# Setting up the NVIDIA Card

To set up the NVIDIA card, you must make sure you have the correct display driver version, install the display driver if necessary, and set the correct display settings.

Prior to setting up the NVIDIA card, check to make sure you have the correct display driver version. If you do not have the 169.47 NVIDIA driver, you can install it from the Utilities folder that installs with your Avid application.

## **To check the NVIDIA display driver version:**

1. Right-click the Desktop and select Properties.  
The Display Properties dialog box opens.
2. Click the Settings tab.
3. Click the Advanced button.
4. Click the applicable Quadro tab. You might have to click the first element in the tree in the tab on the left when you click the Quadro tab, or you have to click the System Information link on the bottom left corner.

The version number is listed in the Graphics card information section on the ForceWare version line.

## **To install the NVIDIA display driver:**

1. Navigate to Program Files\Avid \ Utilities \nVidia and double-click 169.47\_forceware\_winxp2k\_english\_whql.exe.
2. Follow the on-screen instructions to unzip the NVIDIA file to C:\NVIDIA\Win2KXP\169.47.  
The NVIDIA Setup program opens.
3. Follow the on-screen instructions, and then restart your system.

## **To set Dualview mode if you are working with two monitors:**

1. Right-click the Desktop, and select Nvidia Control Panel.
2. In the settings window in the left of the window, click Set up multiple displays.
3. In the “Choose View display mode to use” area, select “Configure independently from each other (Dualview).”
4. Click Apply, and then click OK.

## Disabling the NVIDIA Driver Helper Service (Windows XP)

The NVIDIA driver Helper Service is a background program that runs with the NVIDIA Driver installed. This service informs you when an update to the NVIDIA Driver is available. There have been instances where this service causes slow restarts and shutdown with the Avid DNA hardware attached. The service also can prevent the Adobe® Photoshop® Gamma loader from operating, which causes color correction settings not to work properly. If this occurs, you should disable the NVIDIA Driver Helper Service.

### **To disable the NVIDIA Driver Helper Service:**

1. Right-click My Computer.
2. Click Manage.
3. Double-click Services and Applications.
4. Double-click Services.
5. Right-click NVIDIA Display Driver or NVIDIA Driver Helper Service.
6. Click Properties.
7. Select Startup Type > Disable.
8. Click OK.

Every time you update or reload the driver, this service is enabled again.

# Shared Storage Support

The editing application has been tested in a shared storage environment with the following:

<b>Editing Application Operating System</b>	<b>ISIS Client supported version</b>	<b>ISIS Server supported version</b>	<b>MediaNetwork Client supported version</b>	<b>MediaNetwork Server supported version</b>
Windows XP	v1.4, v1.5, v1.6, v2.0.1	v1.4, v1.5, v1.6, v2.0.1	v4.1.6, v4.2.4, v5.0.1, and v5.1, v5.1.1	v4.1.6, v4.2.4, v5.0.1, and v5.1
Windows Vista Business 32 and Windows Vista Business 64 <sup>a</sup>	v1.5, v1.6, v2.0.1	v1.4, v1.5, v1.6, v2.0.1	v5.1, v5.1.1	v4.1.6, v4.2.4, v5.0.1, and v5.1
Macintosh Leopard 10.5.5 and 10.5.6. See <a href="#">“Compatibility Chart” on page 5</a>	v1.5, v1.6, v2.0.1	v1.4, v1.5, v1.6, v2.0.1	v5.1, 5.1.2	v4.1.6, v4.2.4, v5.0.1, and v5.1

a. Windows Vista Business 32 is supported on some Avid editing applications. See [“Compatibility Chart” on page 5](#).

## Before You Install the Editing Application

Use the following information to determine which editing applications can be installed on your system.

### Existing Editor Upgrades

The following existing editing applications can be upgraded to the following:

- Media Composer versions v2.7.x and higher can upgrade to Media Composer v3.x (on WinXP OS).
- Symphony Nitris versions v1.7.x and higher can upgrade to Symphony Nitris v3.x (on WinXP OS). If you are an Avid DS Nitris and Avid Symphony Nitris Dual Boot customer, you cannot upgrade to Symphony v3.0.
- NewsCutter XP and NewsCutter Adrenaline versions v6.7.x and higher can upgrade to NewsCutter v7.x (on WinXP OS).

If you are a new customer (never installed an Avid editor on your system) you can install the following on an approved WinXP system or an approved Vista system:

- Media Composer v3.0 and higher
- Symphony Nitris v3.0 and higher
- NewsCutter v7.0 and higher

The following upgrade process to the Vista version of the editing application is not supported:

For example, if a Media Composer v2.7.x customer uninstalled the editing application, upgraded the OS from WinXP to Vista, and then tried to install Media Composer 3.x, the installation would fail. The only allowable Vista editing application installation is on a clean Vista system.

The Macintosh version of the Media Composer v3.x release can only be installed on a clean Macintosh with OS X Leopard.

## Notes on Vista OS

Note the following topics if you are running the editing application on the Vista OS.

### Disabling Desktop Compositing

If you are running an editing application on the Vista OS, when the Avid editor is launched you might see a dialog box asking you to disable desktop compositing. You can disable it without adversely affecting the Avid editing application.

You can choose to disable it and continue with your editing session. The dialog will appear once you relaunch the application unless you disable the option.

#### **To disable the desktop compositing:**

1. Access the Control Panel.
2. Double-click System.
3. Click Change Settings.
4. Click the Advanced tab.
5. Under the Performance area, click Settings.
6. Uncheck “Enable desktop composition.”

The dialog box requesting you to disable desktop compositing does not appear the next time you launch the editing application.

### User Access Control Setting

Windows Vista includes User Access Control (UAC), which makes you aware of changes that will be made to your computer letting you decide to allow the changes or not. Avid recommends that you leave UAC ON. This feature is turned on by default in the Windows Vista operating system.

### Standard User

You need to first install the editing application as an Administrator. If you are in a Shared Storage environment, mount your workspaces as an Administrator. You may then log off and log back in as a Standard user, if necessary.

### Vista Windows Sidebar

If the Vista Windows Sidebar is enabled, you might see flickering on the Timeline monitor when you stop playback. You should disable Windows Sidebar:

**To disable the Vista Windows Sidebar:**

1. Right click on the Sidebar or Sidebar icon, and choose Properties.
2. Deselect “Start Sidebar when Windows starts.”
3. Right-click the icon, and choose Exit to close the sidebar.

## New Folder Structure

Some editing application folders have moved to a new location that is now shared and visible to the user on installation. These folders are created at installation time and are given special permissions to work for all users.

The following folders are created on your Windows XP system in the following location:

C:/Documents and Settings/AllUsers/Shared Documents/<AvidProductName>

- Avid Attic
- Avid Users
- Avid Media\_Files
- Avid Templates
- Settings
- Avid FatalErrorReports
- sharedjvm/server/apps/MediaIndexer/stat/log
- MarqueeTitles
- AVX Plug-Ins Data

The following folders are created on your Vista system in the following location:

C:/Users/Public/Public Documents/<AvidProductName>

- Avid Attic
- Avid Users
- Avid Media\_Files
- Avid Templates
- Settings
- Avid FatalErrorReports
- sharedjvm/server/apps/MediaIndexer/stat/log
- MarqueeTitles
- AVX Plug-Ins Data

## Cleaning up Old Folders Before Installation

Do the following to clean up old folders before you install the new ones if you are performing an upgrade.

### To clean up folders:

1. Before installing Media Composer 3.0, you need to uninstall your old version and any version of FilmScribe, EDL Manager, MediaLog, and Avid Log Exchange.
2. Remove the following Registry keys on your system if they still exist after the uninstallation process.

HKLM/Software/Avid Technology/<productname>

HKLM/Software/Avid Technology/AVX Plug-ins

3. From the following folders, remove any folders that do not have custom data in them that you want to keep. If you do have custom data, copy the data to the new locations after step 4.

C:/Documents and Settings/AllUsers/ApplicationData/Avid/<productname>

C:/Program Files/Avid/<ProductName>

(Vista) C:/ProgramData/Avid/<Productname>

4. Install the new Avid editing application.

## Notes on Software Licensing

### If You Upgrade Your Operating System

If you need to upgrade your operating system after you install your Avid editing application, first deactivate your software. After you upgrade your operating system and, if required, reinstall your application, you can reactivate your software. For information on activating and deactivating your software license, see the *Installation Guide for Avid Editing Applications*.

### Laptop Network Settings

Your software license uses information from your system's network configuration. Some laptops disable the Network Interface Card (NIC) when connecting to the Internet through a wireless network connection. If you run your Avid editing application on a laptop, be sure that your NIC and wireless configuration is always the same as when you originally activated your software. See the user assistance for your computer for information on changing network settings.

## Using the GetLicenseInfo Utility

Avid provides a utility program — GetLicenseInfo.exe — that retrieves information specific to your license. This is useful if you no longer have the original license information or if you need to provide this information to Avid Customer Support. The license information retrieved by the utility depends on your system, but it can include the following:

- Avid editing product name
- License type
- Status
- System ID
- Serial number (for security reasons, only part of the serial number is displayed)
- Avid machine ID

### To retrieve license information:

1. Navigate to one of the following locations:
  - ▶ (Windows) Program Files\Avid\Utilities\GetLicenseInfo
  - ▶ (Macintosh) Applications/Utilities/Avid Utilities/GetLicenseInfo
2. Double-click GetLicenseInfo.exe
  - A terminal window opens and displays your license information.
3. Copy the appropriate license information, and then close the terminal window.

## Installing the Software

If you are updating from a previous release, you should uninstall the existing editing application. You should also uninstall Digi Drivers using Add/Remove from the Control Panel. Reboot the system and then install the new editing application. If you do not remove the Digi Drivers, the Audiosuite plug-ins do not load and you might receive either the error message “This software requires installation of device driver TPkd and a reboot before running” or a “DAE Interface NOT Available” error message. If you see these errors on a clean installation on a brand new system, install Hot fix KB926255 from Windows Update to fix the problem.

(Macintosh Only) If you are upgrading from a previous version of the Macintosh editing application, remove the Stereo Mixer.dpm and Surround Mixer.dpm plug-ins from the following location: Macintosh HD/Library/Application Support/Digidesign/Plug-Ins. If you do not remove these files, you might experience problems with the AudioSuite Tool.

For all Avid editing applications, you must first log in as the Administrator (not just a user with administrator privileges), install the application, and initially launch the application as the Administrator. If you are working in a shared storage environment, mount your workspaces. You may then subsequently run the Avid editing application as a regular User.

**(Windows) To install the Avid editing application software:**

1. Quit all active applications.
2. Insert the editing application DVD.
3. Click to Install the Avid Editor Suite or Individual Product and follow the on screen instructions.



*If the FilesInUse dialog box appears, you can safely select Ignore and continue.*



*Depending on Windows activity on your system, some Microsoft Windows Driver Warnings might be minimized into your task bar at installation time. If your installation is taking longer than 5-10 minutes, please check your task bar for an icon with the word SOFTWARE in it. Click the icon and you may safely select Continue Anyway to continue your installation.*

4. When prompted, select “Yes, restart my computer.”

**(Macintosh) To install the Avid Editing application software:**

1. Quit all applications.
2. Insert the editing application DVD.
3. Click to Install the Avid Editor Suite or Individual Product and follow the on screen instructions.
4. When prompted, select “Yes, restart my computer.”

## New in Avid Media Composer v3.5

### What's New

The following outlines the new features for the Avid® Media Composer® version 3.5, NewsCutter® version 7.5 and Symphony™ Nitris® products version 3.5 products. Each feature does not apply to every product model. See the More Info column for links to further details on the feature.

Feature	Description	More Info
Software Activation	Avid is now incorporating a software licensing option for activating your software.	If you are a new customer, the <i>Installation Guide</i> provided in the documentation box provides software activation details. If you are upgrading from a previous release and ordered an upgrade kit, the <i>Installation Guide</i> in the upgrade kit provides software activation details. If you are downloading your software from the Avid download page, see the <code>Install_SWLicense.pdf</code> on the download page for software activation details. Also see <a href="#">“Notes on Software Licensing” on page 16.</a>
Keyframeable Color Correction.	You can now animate most color correction adjustments using advanced keyframes.	See “Keyframing Color Corrections” in the Help.
Long-GOP Video Mixdown	The editing application now supports video mixdown using Long-GOP HD formats.	For more information see <a href="#">“Long-GOP Media Creation” on page 22.</a>
Relink Enhancements	You can now relink clips to any available SD or HD media and select the format and resolution within the Relink dialog box.	See “Relinking Media Files” in the Help.
Native Thin Raster Support	On some system configurations you can directly select the raster size used for playback and editing.	See “Raster Sizes” in the Help.
BWF Audio File Support	You can now import multi-channel, monophonic BWF files into an Avid editing system as a single master clip.	See “Working with BWF Files” in the Help.
Adjusting Audio Gain Before Import	When you import audio files, you can now set the gain on a clip without opening the Audio Mix tool.	See “Adjusting Gain Before Importing Audio Files” in the Help.
Avid Media Access (AMA) Plug-In Architecture	Allows you to link clips (XDCAM, XDCAM EX, and P2) from a third-party volume into a bin without storing the media directly onto your system.	See “File Based Media” in the Help.

Feature	Description	More Info
XDCAM EX	You can now import an XDCAM EX clip into an Avid editing application or use the AMA method to link to an XDCAM EX clip.	See “Sony XDCAM EX Media” in the Help.
XDCAM	Added improved performance to the speed of XDCAM imports on both the Windows and Macintosh platforms.	See "Sony XDCAM Media" in the Help.
FluidStabilizer	A new tracking engine specifically designed to track camera motion.	See “Stabilizing an Image” in the Help.
Modifying Sequences that Include Effects	This release adds several new or modified menu commands.	See “Promoting and Demoting Existing Effects in Sequences” in the Help.
Advanced Keyframe Changes	<p>This release makes the following changes to advanced keyframe functionality:</p> <ul style="list-style-type: none"> <li>• The Automatic Start and End Keyframes setting is no longer available in the Effect Editor settings</li> <li>• The way that nested advanced keyframe effects behave in the Effect Editor has changed</li> </ul> <p>All nested effects on a segment are now fully available in the Effect Editor. You can open and manipulate the available parameters and keyframe graphs for any nested effect at any time.</p> <p>The old mechanism for changing the order of nested effects in the Effect Editor by dragging nesting priority icons is no longer available.</p> <ul style="list-style-type: none"> <li>• <i>If you have nested standard keyframe effects in a sequence, the Effect Editor shows only one effect at a time. If you have a mix of standard keyframe and advanced keyframe effects in a nest, effects below the standard keyframe effect do not show in the Effect Editor unless you step into the nest.</i></li> </ul>	See “Working with Advanced Keyframes” in the Help.

Feature	Description	More Info
New Parameters for Generator Effects	New options have been added to the SubCap and Timecode Burn-In effects.	See “Generator Effects” in the Help.
Stereoscopic	This feature allows you to display and edit stereoscopic (3D) material.	See “Working with Stereoscopic Material” in the Help. The settings that control your monitor setup for stereoscopic editing are user settings rather than project settings. This might be inconvenient, for example, when you switch between a 3D and a non-3D project. Consider creating a user profile specifically for stereoscopic work that you can switch to whenever you load a stereoscopic project.
16-Channel Audio	The Capture Tool now supports capture of up to 16 audio channels of HD-SDI input from supported HD devices.	See “ <a href="#">HD-SDI 16-Channel Audio</a> ” on page 22.
AudioSuite Plug-Ins	This release provides support for additional AudioSuite Plug-Ins.	See “Understanding Digidesign AudioSuite Plug-Ins” in the Help.
CPU/GPU Acceleration	With this v3.5 and v7.5 release, additional effects take advantage of the CPU/GPU acceleration.	See “ <a href="#">CPU/GPU Acceleration</a> ” on page 22.
Change to 3GB Utility Procedure.	You should set the amount of memory you want to allocate for the application space on a Mojo DX and Nitris DX to 2700 instead of 2500 as stated in previous releases. You will receive a reminder message when you launch the editor if attached to a Mojo DX or Nitris DX.	See “ <a href="#">Extending Your Usable Address Space and Adding RAM for Improved Performance (Windows)</a> ” on page 61
Exporting improvements	Avid supports embedded timecode when you export to XDCAM.  Avid supports embedded timecode when you export a QuickTime movie.  Avid supports exporting 8 tracks of audio to MPEG IMX and XDCAM HD 50 Mbits.	

## Long-GOP Media Creation

Avid editing applications now allow full media creation and playback support for all of the specified Long-GOP formats and modes (XDCAM HD and XDCAM EX). This includes support for video mixdown using Long-GOP HD formats.

For more information on using Long-GOP formats in your projects, see “Long GOP Workflows” in *Avid Interplay Best Practices v1.6*.

## HD-SDI 16-Channel Audio

The Capture Tool now supports capture of up to 16 audio channels of HD-SDI input from supported HD devices. You can also enable up to 16 audio channels in the Digital Cut tool for insert edits when you use HD-SDI output.



*Not all decks support 16-channel audio. See the product documentation for your deck for more information.*

The HD-SDI 16-channel output is available for Avid editing systems using the following Avid input/output devices;

- Avid Nitris DX
- Avid Mojo DX

## CPU/GPU Acceleration

With the v3.0 and v7.0 releases, CPU/GPU acceleration of visual effects was introduced. The system automatically uses the available CPU and GPU resources in the host workstation to accelerate effects performance. With the v3.5 and v7.5 release, additional effects take advantage of this CPU/GPU acceleration. New GPU effects include 3D-Warp Perspective, SpinZ, Luma Key, and Peel.

And in the Render Settings options, the “Effects Quality Render Using” option has been changed to “Image Interpolation”. Note, the standard mode was the only quality mode supported in the previous release, except for Symphony Nitris.

---

Image Interpolation Sets a global override for effects that resize or reposition. The following options are available:

**Advanced (Polyphase):** Causes effects to use the highest quality.

**Standard (Bilinear):** Causes effects to use the standard high quality.

**Draft (Nearest Neighbor):** Causes effects to use highest performance option though not necessarily finishing quality.

---

## Fixed in Avid Media Composer v3.5

The following have been fixed.

- **Bug Number:** UDevC00111120. You might have received a "DIG\_TOO\_SHORT" error when performing a batch capture in a 720p 59.97 project in an Avid Unity ISIS environment. This has been fixed.
- **Bug Number:** UDevC00116346. Previously, you could not perform a digital cut of DVC PRO HD media to a Panasonic AJ-HD1400 deck. This has been fixed.
- **Bug Number:** UDevC00111136. You may have received an error if you renamed a folder in the Project window and then saved a bin that resided inside this folder. This has been fixed.
- **Bug Number:** UDevC00106907. (Macintosh) You might have received "Segmentation Fault" errors when using JKL on a MultiGroup clip. This has been fixed.
- **Bug Number:** UDevC00111130. Previously, when working with the SpectraMatte effect with DNxHD 220 media and the Video Quality option for playback was set to Full Quality-10 bit, the application was extremely slow. This has been fixed.
- **Bug Number:** UDevC00116233. If you moved from Avid Unity MediaNetwork to Avid Unity ISIS, you might have experienced a delay on playback of 9 way MultiCam. This has been fixed.
- **Bug Number:** UDevC00111126. If you had filler at the beginning of a sequence and changed the display in the Timecode burn-In effect, the editing application might hang. This has been fixed.
- **Bug Number:** UDevC00119156, UDevC00112015. If an AVX1 effect was sitting directly on a filler clip, both the effect and the filler would disappear during the promotion. This has been fixed.

- **Bug Number:** UDevC00111035. Previously, exporting a QuickTime reference took longer to complete than in previous versions of the editing application. This has been fixed.
- **Bug Number:** UDevC00106168. Previously, an Avid Symphony Nitris system in an Avid Interplay v1.2.3 environment might drop frames when playing uncompressed video. This has been fixed.
- **Bug Number:** UDevC00116129. MetaSync enhancement matte keys were not importing correctly. This has been fixed.
- **Bug Number:** UDevC00116532. VFX and DPX Timecode was not appearing in the Record Monitor Timecode display or the Timecode window. This has been fixed.
- **Bug Number:** UDevC00113870. (Symphony Nitris DX) You might have received a "Get Free Heap" error when memory exceeded 17%. This has been fixed.
- **Bug Number:** UDevC00106279. Previously, the application might not check for offline media prior to starting a Digital Cut. This has been fixed. However, if your sequence contains a meta track, you might still get an offline media message.

## Limitations and Known Issues

### AMA (Avid Media Access)

- **Bug Number:** UDevC00122070. If you apply an AudioSuite Plug-in to an XDCAM EX clip linked through AMA, the system freezes when you attempt to render.  
  
**Workaround:** Consolidate the media before you render, or do not install AudioSuite Plug-ins if you plan to link to XDCAM EX media.
- **Bug Number:** UDevC00120470. When linking clips through AMA, the metadata information might be missing when you switch from Brief view to Text view in a new bin.  
  
**Workaround:** Link the clips through AMA when the bin is in Text, Script, or Frame view.
- **Bug Number:** UDevC00118383. P2 AMA import: On some projects such as 1080i59, the editor may not be able to consolidate or transcode from spanned P2 cards. The system displays the following error message: ConsolidateFMobs() Too Many Files. Workaround: If you encounter this problem, use the non-AMA method for importing media from spanned P2 cards.

- **Bug Number:** UDevC00119182. While working in AMA, the Bin Column Selection dialog box doesn't always display all the bin headings.

**Workaround:** Close and reopen the bin where the AMA clips are stored. The bin headings should all appear in the Bin Column Selection dialog box.
- **Bug Number:** UDevC00121158. Keep the target audio sample rate the same as the native audio sample rate when you consolidate or transcode a clip using AMA. If you choose to convert the audio sample rate, the system does not calculate the needed space requirement and the consolidate fails. You can however choose to convert the audio sample bit depth or convert the audio format for a successful consolidate to occur.
- **Bug Number:** UDevC00120055. The Avid editing system might be slow to respond while mounting multiple workspaces, while in the application, in AMA (Avid Media Access).

**Workaround:** Mount the multiple workspaces prior to opening the Avid editing application, and then work in AMA.
- **Bug Number:** UDevC00119615. (Macintosh only) Offline clips appear selected (highlighted yellow) even after you eject a write-protected XDCAM EX (SxS) card.

**Workaround:** Do not write-protect the card and do not eject the card while the application is running.
- **Bug Number:** UDevC00115894. Playing back XDCAM DV 25 media from a disc might drop or skip audio frames, this could be due to the disc needing time to spin back up.
- **Bug Number:** UDevC00116263. The following folder names: “OMFI MediaFiles,” “Avid MediaFiles,” “Contents,” “Clip,” and “BPAV” are application or camera generated file names which contain data appropriate media files. To avoid assertion failure errors when mounting volumes, do not create additional folders with these file names on your system.
- **Bug Number:** UDevC120470. When you link clips through AMA, make sure the bin is in Text, Script or Frame view. The metadata bin headings will not save in Brief view.

## Audio

- **Bug Number:** UDEV00220668. If your system is an HP xw8400, you must customize the sound configuration in order for the editing application to correctly control the levels of the microphone or other connected audio device:

**Workaround: To customize the sound card configuration:**

1. In the Project window, click the Settings tab.
2. Double-click Sound Card Configuration.
3. Ensure that the Record/Input descriptions match the Playback/Output settings. For example, if you have a microphone plugged into the rear pink connector, then the Playback/Output option should be set to Rear Pink In. If you have a Line input audio device connected to the front black connector, the Playback/Output option should be set to Front Black In.

- **Bug Number:** UDEV00143962. Clip Pan: When you add an audio dissolve between two clips with Clip Pan onto a single audio track, the audio dissolve uses the Clip Pan setting on the outgoing source for the duration of the dissolve.
- **Bug Number:** UDevC00118578. Occasionally, you might receive a "ReadStreamAsyn" error when performing a Digital Audio Scrub. If you continue scrubbing, the audio will come back.
- **Bug Number:** . Pan Automation (overrides Clip Pan when applied): When you add an audio dissolve between two clips with Automation Pan onto a single audio track, the audio dissolve interpolates the pan values between the pan keyframe value at the beginning of the dissolve and the pan keyframe value at the end of the dissolve. Any pan keyframe that exists in the middle of the dissolve is ignored.

**Workaround:** Place the two clips on separate tracks using Clip Pan, fade one to silence, and fade the other up from silence.

- **Bug Number:** . If you open a 720p50 HD project, open the Capture tool window, select HD-SDI video and Audio input. Capture an HD Clip from Satellite source using HD-SDI Embedded feature, saved it to Bin. Create an HD sequence using above saved HD Clip. Configure the Panasonic HD 150, set the deck to accept HD-SDI audio Embedded. Open Video output dialog: Turn on HD-SDI Audio Embedded ON. Attempt to output an HD sequence (Preview) to a HD deck using HD-SDI audio Embedded feature completely fail. There is no audio output signal seen on Deck.
- **Bug Number:** UDEV00207753 . The Panasonic HD150 deck will not decode the HD embedded audio stream from Adrenaline or Avid Nitris.

**Workaround:** Connect AES audio from the Avid DNA hardware to the deck and disable the embedded audio.

## Audio Punch-In Tool

- **Bug Number:** UDEV00086862. You could monitor input during preroll in previous versions. If you have a software-only system, you can still monitor input during preroll. If you have an Avid Mojo, input monitoring begins at the IN point, not during preroll.

## Avid Unity

- **Bug Number:** UDevC00107470. (Macintosh) Avid editing clients cannot capture 8-bit 1:1 HD media to a mirrored Avid Unity MediaNetwork workspace; 10-bit HD media works fine.

**Workaround:** To capture 8-bit 1:1 HD media to an Avid Unity MediaNetwork workspace, you must unmirror the workspace then capture the 8-bit HD media. You can then mirror that workspace after the 8-bit 1:1 HD media is captured. Synchronize the workspace with the Administration tool after the mirroring is re-applied.

- **Bug Number:** UDevCC00080420. Avid Unity MediaNetwork and Power User login: If you log into your Windows system as a Power User and use the same login in the Connection Manager to log onto Avid Unity MediaNetwork, you won't be able to play media.

**Workaround:** In order to use an Avid editing application in Interplay you must log in as a Power User. However, do not use the same login when you use the Connection Manager to log onto Avid Unity MediaNetwork. Use a different login for the Connection Manager. This problem does not exist on Avid Unity ISIS.

- **Bug Number:** UDevC00089671. Workspace names in Asian characters might appear truncated at the end in any drive-selection list.

**Workaround:** Use no more than 5 characters for workspace names.

- **Bug Number:** UDEVC00089275. Changing Users on MediaNetwork Fibre attached clients: When you change users on a fibre attached client, do not use the Switch User function in the Windows Log Off dialog box. When you log back in as the original user you may get the following errors when you play media: "Exception: FILE\_OTHER, filename... Exception: SYS\_ERROR, status:1317, msg:The specified user does not exist."

**Workaround:** To fix the problem once it occurs, reboot the system. To avoid the problem, before you switch users, log off completely and reboot the system.

## Capture

- **Bug Number:** UDevC00117699. When performing captures over FireWire with the SonyZ7U or Canon XH-G1 camera, you might receive "Lack of progress" errors.

- **Bug Number:** UDevC00094480. If you have problems with batch capture accuracy for footage captured over 1394 due to undetected small timecode breaks, select the “Enable detection of small timecode break” option located in the Capture Settings DV& HDV tab.
- **Bug Number:** UDevC00116442. A 1:1 10 bit capture might fail with DIG\_VDM\_OVERRUN or video overrun errors. This might not occur if storage performance is optimized.
- **Bug Number:** UDevC00080115. (Macintosh) You might receive a “Mac Error - 37” error when accessing a target drive or workspace with 28 or more characters.

**Workaround:** Make sure the target drive or workspace names are fewer than 28 characters.

- **Bug Number:** UdevC00025851, UdevC00049993. If you capture clips with an Avid editing system on two or more days and use the same project and the same tape name (for example, if you capture on two separate days from a cable feed named “Live”), relinking the clips might cause the old clips to relink to the new clips. Because the clips in this instance are captured on different days but use the same 24-hour timecode and have the same tape name, the Avid system treats the captured material as coming from the same source. When you relink the clips, they relink incorrectly.

**Workaround:** Avid recommends that you avoid using generic or nondescriptive tape names — for example, do not use the tape name “Live” for a live feed. Instead, use distinctive tape names for each capture. Also, you can use separate projects when capturing with your editing system. When you change projects, even if you use the same tape name for your captures the Avid system generates new source IDs. This prevents the relink problem.

- **Bug Number:** UDevC26084. If you are working with DV tapes in the Sony HVR-M10U you might experience “failed to find preroll errors”.

**Workaround:** Change the machine template to the “Generic\_DVDevice-NTSC” or “Generic\_DVDevice-PAL” template. This will force the software to use a different method for cueing to the preroll timecode.

- **Bug Number:** UDEV00225379. The editing application does not warn you if you try to send a Frame Chase editing clip to Media Services Transcode. Do not send ingesting clips to Media Services Transcode. Wait until the clip is completely ingested.
- **Bug Number:** UDevC00086768. You might see the following error message when loading a clip captured by Frame Chase capture in the editor: “Error encountered during relink process: New track length does not equal original track length.”

**Workaround:** In the editing application, right click the clip and sequence and select Update from Interplay. In Assist, refresh the clip from the Interplay database by selecting the clip and pressing F5.

- **Bug Number:** UDEV00195662. When you are capturing and using the passthrough monitor, desktop passthrough might cover error messages that are in the same space as the passthrough monitor, preventing you from being able to read them.

**Workaround:** Move the affected window or message box away from the Record monitor, put another application in front of the Avid application, and then go back to Avid to force the UI to refresh.

- **Bug Number:** UDEV00220761. When you capture from an HDV device through 1394 into an HDV interlaced project, you might see the video break up into squares. The captured media is intact and complete, however.

- **Bug Number:** UDEV00197055. When you capture media that includes invalid frames, you might see an error message that the capture has been aborted and the invalid frames discarded; it asks you if you want to keep the clip. This message is incorrect; the invalid frames have not been discarded.

**Workaround:** Click No to discard the clip, and then recapture using new marks that exclude the bad sections on the tape. Do not keep the clip.

- **Bug Number:** UDEV00204777. When you deselect Enable Confidence View in the Video Display Settings dialog box and then open the Capture tool, the Client monitor does not display passthrough.

**Workaround:** Do one of the following:

- ▶ Select Enable Confidence View.
- ▶ Click the Capture button in the Capture tool.

- **Bug Number:** UDEV00184515. In an HDV project, you can only capture audio at the 48k sample rate. Because the incoming audio is digital over FireWire®, the software is unable to up-sample 32k and 44.1k audio reliably during capture. If you try to capture audio at another sample rate, you do not receive the error message warning that the audio on the tape does not match the setting in the Audio Project Settings dialog. Currently, only the 48k sample rate is supported in the HDV project format.

- **Bug Number:** . If you lose connection to your 1394 port or receive “OHCI Port Busy” errors, check the FireWire cable length.

- **Bug Number:** . When you capture HDV, the system might not find the preroll point if the Preroll setting is set to 3 or below. The default is set to 6. Do not set this option to 3 or below.
- **Bug Number:** UDEV00183907. (HDV) Passthrough does not work if Delay Audio is set to 7 frames or greater. (The Delay Audio option appears in the Capture tool.)

**Workaround:** Set Delay Audio to 6 or fewer.

- **Bug Number:** UDEV00181815. Drop frame/Non-drop frame mismatch errors occurred often when capturing. A new Deck Preference setting has been added. Access the Deck Preferences Settings dialog box. A new “When the deck contains no tape Log as” option appears. Select the timecode format (Drop Frame or Non-drop Frame) for logging clips when no tape is in the deck. When a tape is in the deck, the system automatically uses the existing timecode format on the tape.
- **Bug Number:** . (HDV) When switching from one project format to another while connected to an HDV device, you must turn the HDV device off and then turn it back on again.
- **Bug Number:** . (Windows) If after initially setting up a DV deck for the first time, or after a system recovery you cannot see the deck, manually register the DV buffers file by doing the following:

**Workaround:**

**Perform the following:**

1. Go to Program Files\Common Files\Avid.
  2. Right click Dvbuffers.ax.
  3. Select Open.
  4. Choose to select the program from a list and click OK.
  5. Browse to windows/system32.
  6. Select regsvr32.exe.
- **Bug Number:** UDEV00145432. The following error message, “Exception: ADM\_DIO\_ERROR\_OCCURRED, DIOerr:Expected DV50 NTSC but received DV25NTSC” appears if you attempt to capture DV 25 from a DV 50 source or DV 50 from a DV 25 source.
  - **Bug Number:** UDEV00139553. When you batch capture long clips with a lot of metadata, the following error appears and no media is captured: “Exception: MXFDomain::SaveMetaDataToFile - Failed to save meta data to file.” This does not occur when you batch capture OMF.

- **Bug Number:** . When you capture from a Panasonic AJ-SD93P or Panasonic AJ-SD93E, note the following: the Panasonic default for DIF SPEED is set to S400. The Adrenaline and Avid Mojo expect a DIF SPEED of S100. Capture fails, producing scrambled or blocky images.

**Workaround:** From the Panasonic DVCPRO deck's menu, set the menu DIF SPEED to S100.

- **Bug Number:** . When you capture DVCPRO HD from a Panasonic HD 1200A deck, keep the menu DIF SPEED set to S400.

## Compatibility

- **Bug Number:** UDevC00121033. Playing back EVS media on a Symphony Nitris (classic) is not supported. Playback is supported for Symphony Nitris DX.
- **Bug Number:** UDevC00110632. (Windows) If you are running a Digidesign audio device, such as the Mbox 2, with the editing application and that device appears to be inactive:

**Perform the following:**

1. Quit the editing application.
2. Run the Digidesign Audio Drivers Installer Program in the Avid Utilities Folder.
3. Reboot the system.
4. If the audio device is still inactive, access C:\Program Files\Digidesign\Drivers\DigiDriver.exe and select “Install.”

For Windows Vista 64, the location is C:\Program Files(x86)\Digidesign\Drivers\DigiDriver.exe.

- **Bug Number:** UDevC00100881. You cannot connect to a Sony e-VTR device when using e-VTR manager on a Microsoft Vista32 or Vista64 systems. The Sony e-VTR logging application does not support Vista.
- **Bug Number:** UDevC00119004. Previously, the Best Performance Video Quality option (yellow/yellow) was the only option available when working with HD projects in MultiCamera Mode. The yellow/green video quality option is now available in MultiCamera Mode when working with HD projects.
- **Bug Number:** UDevC00112765. Currently, it might take longer to load a LongGop 9-way or Quad Split source view.

- **Bug Number:** UDevC00105042. IMPORTANT: If you make a change to the project type or the raster type, the settings in the Video Output tool will change to the application default settings. For example, if you had Sync Lock set to Reference and you changed the project type or the raster type, the Sync Lock setting would change to the default (Internal). If you make a change to the project type or raster type go to the Video Output tool and make sure the values set in the Video Output tool are the desired settings.
- **Bug Number:** UDevC00105849. If you open the Audiosuite tool when unlicensed plug-ins are installed, the system will lock up.
 

**Workaround:** Either remove the demo or unlicensed plug-in from your system. Or connect the iLok dongle that has the valid license key to the system.
- **Bug Number:** UDevC00104160, 00024645. If your original project was a 1080i50 or 1080p25 project, when you are working in a 25i PAL project, the bin headings for MPEG 30 and MPEG 50 might not be accurate.
- **Bug Number:** UdevC00102207. (Macintosh) If you find that your mapped F keys are not working, go to System Preferences > Mouse and Keyboard > Keyboard tab and make sure “Use F1-F12 keys to control software features” is checked.
- **Bug Number:** 99387. Currently, if you are exporting a QuickTime movie and select the Custom option, you might receive an Access Violation and a Structured Exception loop dialog. You must force quit the application or select Abort on the Structured Exception dialog box. In QuickTime player, go to Edit > Preferences > QuickTime Preferences, then select the Advanced tab and select “Safe mode (GDI only)” under video.
- **Bug Number:** UDevC00098170,UDevC00098065. If you are working on a standard-definition (SD) project with an Avid Nitris DX or Avid Mojo DX attached to your system, you cannot use the Best Performance mode for video playback. If you open an SD project created on a system with an Avid Adrenaline attached and utilize Best Performance mode, the Avid Nitris DX system promotes the video quality to Draft Quality. Either click the Video Quality button and select Draft Quality or Full Quality, or change the project type to the appropriate high-definition format.
- **Bug Number:** UDevC00099354,UDevC100032. The VBI (Vertical Blanking Interval) option in the Video Output tool allows you to blank or to preserve 5 lines above each field for NTSC and 8 lines for PAL when you perform a digital cut. The VBI option is not available on systems connected to an Avid Nitris DX or Avid Mojo DX input/output device.
- **Bug Number:** UDevC00101326. Currently, if you export a QuickTime movie and convert the sample rate on export, it might result in bad audio.

- **Bug Number:** Udevc00101033. (Adrenaline, Vista) If you are running your editing application on the xw8400 or xw8600 computer you must have the HP 1394a FireWire card (Avid PN 7030-20154-01; HP PN PA997A) or the Sonnet Technologies™ Allegro™ FW400 1394a FireWire card installed. You may experience "Huffman Decode" errors during batch capture or capture on-the-fly if you run with an unapproved Firewire card.
- **Bug Number:** UDevC00097564. Currently, if you are on a Vista 64 editing application and you try to open a bin that was created on a Windows XP editing application, you might receive an "Unable to open file" message. The issue is that when you move a file from the desktop to the project folder, it loses access rights. Access the file as an administrator and add Authenticate Users with Full Control.
- **Bug Number:** UDevC00093513. (Macintosh) The editing application might not launch if your system volume name contains "/" . Make sure the computer volume name does not include a "/".
- **Bug Number:** UDevC00090317. A non Administrator cannot send or receive EDLs. You must be an administrator to use EDL Manager.
- **Bug Number:** UDevC00079997. (FilmScribe) The Tape Name does not appear in a cut list when you select the TapeID column heading.  
  
**Workaround:** If you select both the Reel# and TapeID column heading, the Tape Name appears.
- **Bug Number:** . (Macintosh) When you are using the search feature in the Avid editing application Help, a bug exists if Safari™ is your default browser. You might experience issues when performing searches. You need to empty the Safari cache in between searches (Select Safari > Empty Cache.) This search issue does not occur when you use Firefox™ as your browser.
- **Bug Number:** UdevC00007737. If you are using an Mbox 2 and an HP8400 computer, you should connect the Mbox 2 to a rear USB port. The USB ports on the front of the HP8400 can cause problems with the Digidesign Driver Installer. Once the installation is complete, you can connect the Mbox 2 to the front or rear USB ports.
- **Bug Number:** UDEV00140811, UDEV00140767, UDEV0221008. If you are using the Safari browser to access the Avid Learning Excellerator™ site (select Help > Learning Resources, and then click the Avid Learning Excellerator link), you must have Javascript® and cookies enabled (Safari > Preferences > Security).

- **Bug Number:** UDevC00052206. Due to changes in Avid Media Composer v2.5.x (Macintosh), some third party AudioSuite and AVX plug-ins may not load properly. This is due to moving the Avid editors to Xcode® from CodeWarrior™ 9 for support of the new Mac Intel® based systems. Customers may need to upgrade their AudioSuite and AVX plug-ins. Please note that Avid has informed Third Party partners of this change. Third Party plug-ins that have not been updated will not be supported in this release.
- **Bug Number:** UDevC00079523. If you are a non-administrator and you want to launch AudioSuite Plug-Ins, make sure you have an administrator make you a member of the AvidUsers group which is automatically created during installation.
- **Bug Number:** UDEV00219672. You currently cannot select HDV projects in the MediaLog™ application.
- **Bug Number:** UDEV00164891. (NewsCutter XP Software Only) When working with the HP/Compaq nw8000 laptop, if you press the volume button (which is located on the front of the laptop, not on the keyboard), this causes an overwrite in the source/record edit to the Timeline.
- **Bug Number:** UDEV00141328. Sending to Digidesign® Pro Tools: When you export an OMF 2.0 file that links to MXF media, you should first transcode the MXF Media to OMF media. If you have a long sequence containing MXF media, you are not prompted prior to the export process that the export will not be successful. To save time, transcode MXF media to OMF media prior to exporting as OMF 2.0.
- **Bug Number:** UDevC00091387. Due to an issue with the RICOH FireWire controller on the Dell M65 and M90 laptops, when playing out to the host in 1394 mode, as well as a DV device via the “Output to DV Device” option, video and audio may drift out of sync.
 

**Workaround:** Turn off “Output to DV Device.” Or, if you have to use the DV Device for monitoring, connect the speakers or headphones to the DV device/camera instead of the PC.
- **Bug Number:** UDevC00120475. Editing keyboard shortcuts such as Ctrl+X and Ctrl+C do not work in MetaSync Manager. Use the menu commands.

## Digital Cut

- **Bug Number:** UDevC00102676. When performing a digital cut, you will receive the message “If you have a genlock signal connected to your BOB, please switch it to match the output rate. Use an appropriate black burst sync source. Then wait for the REF light on the BOB to turn green and press Continue.” If the light turns green, press Continue and the digital cut will be performed. If not, make sure an appropriate sync source is connected and wait for the REF light to turn green.

- **Bug Number:** UDevC00097111. (Avid Nitris DX/Avid Mojo DX) Currently the blue bar in the Timeline might not reach the end of the sequence at the end of a digital cut. All frames are actually cut to tape.
- **Bug Number:** UDevC00118267. A “Media Offline in Composition” error might occur with a Digital Cut even when all media is online. Select Continue to perform the Digital Cut.
- **Bug Number:** UDEV00222537. (Macintosh) When performing a 720p/59.94 digital cut, the first frame of the sequence might be missing.

**Workaround:** Add half a second of black before the sequence.

- **Bug Number:** UDEV00220887. The first 35 frames of a sequence might be missing when you perform a digital cut after selecting Crash Record and Ignore Time in the Digital Cut tool.

**Workaround:** Add filler to the beginning of the sequence.

- **Bug Number:** UDEV01845957. When performing an HDV digital cut, the last few seconds are not cut to tape.

**Workaround:** Generate a clip of black and add it to the end of the sequence.

- **Bug Number:** UDEV00174311. A digital cut of an HD project might drop the last frames of audio.

**Workaround:** Add 10 frames of audio to the end of the sequence.

- **Bug Number:** UDEV00135921. When you perform a digital cut using the Pioneer® PRV-LX1 DVD recorder, select Ignore Time in the Digital Cut Tool window.

- **Bug Number:** UDEV00136395. A video underrun might occur at the start of a digital cut if the Digital Cut tool does not have focus when you click the Play Digital cut button. The Digital Cut window must be active before you click either the Start or Preview button. If an underrun occurs at the very start of the digital cut, you should be able to perform the digital cut without a problem.

- **Bug Number:** UDEV00139484. When you perform a digital cut to a Panasonic DVCPRO HD deck using HD-SDI with 720p/59.94 material, several frames of black might be written to tape before the start of the outputted sequence. This might result in the end of the sequence being truncated on tape.

**Workaround:** Place several seconds of black or color bars at the end of a sequence.

- **Bug Number:** UDEV00138162. The Digital Cut tool does not allow certain durations of black to be added to the tail of a sequence. Certain values (including 20 minutes, 30 minutes, 60 minutes, and so on) reset the clock to zero when applied. If the value you entered resets to zero when applied, adjust the value upward or downward until a satisfactory length is determined (at which point the clock does not reset itself and the desired duration is correctly applied).

## Dynamic Relink

- **Bug Number:** 103557. Any MPEG2 352\_30I MXF media created with an x.8.1 or x.8.3 editing application will not relink in Exact match in versions x.8.4 of the editing applications or the Media Composer 3.0 or Symphony 3.0 or NewsCutter 7.0 versions of the editing application. The MPEG2 352\_30I MXF media created with an x.8.1 or x.8.3 was compressed at 15MB instead of 2MB and therefore will not relink in Exact match.

**Workaround:** Change the Dynamic Relink settings to use the “Most compressed” option or change the “If no match is found” option to “Relink to Closest.”

- **Bug Number:** UDEV00225796. When working with HDV projects, HDV resolutions are not available for Dynamic Relink.

**Workaround:** Choose “Use Closest Media” instead of “Relink to Offline” when in HDV projects and “Specific Resolution” is selected as the Relink Method. If you do not choose “Use Closest Media”, captured clips appear as offline when Dynamic Relink is enabled.

- **Bug Number:** UDEV00221144. If you want to re-create title media at a target format other than the working format, you must change the project format to that designated for the target, otherwise only the working format resolutions are available.

## Effects

- **Bug Number:** UDevC00118276. You might experience dropped frames on the initial playback of a sequence containing a Pan and Scan effect.

**Workaround:** Set the Image Interpolation option in the Render Settings to Standard (Bilinear).

- **Bug Number:** UDevC00112035. You might receive a bus error when exporting a sequence in a 24p NTSC project that contains a scratch removal effect. Render the sequence first.

- **Bug Number:** UDevC00117131. Currently, you cannot preview Multi channel audio clips with AudioSuite Dynamic 3 plug-in effects. The plug-ins work in the Timeline.

- **Bug Number:** UDevC00117990. If you try to conform an AFE created from the Avid Media Composer or Avid Symphony editing application to Avid DS, the Color Correction animation effects will not conform. The effects will be replaced with a wipe effect. You should demote the color corrections. Right-click the sequence that contains the Color Correction effects and select Demote Effects. This creates a duplicate sequence that you can open in Avid DS.
- **Bug Number:** UDevC00114633. When you apply a SubCap or TimeCode Burn-In effect to a clip with the Effect Editor set to Thumbwheels, the first few characters in the text field are cropped from view. They do appear properly on the image.
- **Bug Number:** UDevC00113832. Applying Boris Continuum Complete deinterlace above other effects might corrupt the image.
- **Bug Number:** UDevC00115301. You might receive an “AudioSuite DAE” error when you render a master clip with a ReelTape AudioSuite Plug-in. The error does not occur if you render in the Timeline.
- **Bug Number:** UDevC00118588. The Tracking window becomes deselected after switching from a nested effect to the top-most effect. You must close and then reopen the Tracking window to make it available.
- **Bug Number:** UDevC00118505 . Currently, a Superimpose or Dissolve effect does not promote to 3D Warp.
 

**Workaround:** First promote to Advanced Keyframe, then to 3D Warp.
- **Bug Number:** UDevC00109451. When the Color Correction window is open, Loop Play will include the sequence, not just the current clip, even if the Effect Editor is open.
- **Bug Number:** UDevC00120950. You might experience dropped frames when playing back an HD sequence containing a Safe Color limiter effect with the “422 Safe” option selected.
- **Bug Number:** UDevC00113368. When working in 3D Advanced keyframes, occasionally, keyframe points might not display in the path.
 

**Workaround:** Click the Enlarge or Reduce button located below the Effect Preview Monitor.
- **Bug Number:** UDevC00106944. In a 1080i59 project, effects that invert or resize the image might appear field-reversed during play in an SD timeline.

**Workaround:** Transcode the media to SD.

- **Bug Number:** UDevC00097157. A clip with an unrendered TimeWarp effect might not import to ProTools. Render the effect before exporting.
- **Bug Number:** UDevC00090708. If you try to run AudioSuite and receive the following message, “Your computer is missing a Windows XP update required by ProTools. Please install all available critical updates before installing ProTools” you must perform a Windows Update, Custom Install to ensure the correct dll is installed.
- **Bug Number:** UDevC00003573. While in Effect mode, you might not be able to scrub through blue dot effects and have the monitor update. Move the Effect Editor so that it overlaps some part of the Composer monitor. The monitor should now update correctly when you scrub through blue dot effects.
- **Bug Number:** UDevC00100286. Currently, AAF cannot conform Pan and Scan correctly. Output an AFE.
- **Bug Number:** UDEV00225614. Safe Color limits might be exceeded in SD downconverted output from an HD project. In an HD project, if you use the Safe Color Limiter effect to ensure safe colors in a sequence and then output that sequence using SD downconvert, some transient pixel values might exceed your safe color ranges. This is a consequence of the resizing process performed in the Avid Nitris or Adrenaline hardware during an SD downconvert.

**Workaround:** Change the project type to an SD type before you output or render the sequence.

- **Bug Number:** UDEV00219374. In 30i or 1080i60 projects, Timewarp effects that use the Film With 2:3 Pulldown Input format might not render correctly. Some frames might remain unrendered or it might not be possible to complete the render. This problem is known to occur in the specific circumstances described below, but might also occur in other circumstances.

**Partial Render.** The problem might occur if you perform a partial render of a Timewarp effect using the Film With 2:3 Pulldown Input format, then render the remaining part of the segment. Some frames might remain unrendered or the second part of the segment might not render.

**Division of rendered segment.** The problem might occur if you render an entire Timewarp effect using the Film With 2:3 Pulldown Input format, and then divide the segment (for example, by performing an overwrite edit of new material into the middle of the segment). Some frames in the second part of the divided segment might become unrendered.

**Trimming head frame of rendered segment.** The problem might occur if you render an entire Timewarp effect using the Film With 2:3 Pulldown Input format, and then trim the head frame of the segment. Some frames in the segment might become unrendered.

- **Bug Number:** UDEV00207851. You might not be able to render a FluidBlur, FluidColorMap, or FluidMorph effect in an HD project if there is not enough memory available.

**Workaround:** Try one of the following:

- ▶ In the Bins tab of the Project window, click the Clear button, and render the Fluid effect (see “Managing Bins and Memory” in the Help).
  - ▶ Close all unused bins, relaunch, and render the Fluid effect.
  - ▶ In the Format tab of the Project window, switch the project format to an SD format, render the Fluid effect, then switch back to HD.
- **Bug Number:** UDEV00221706. Very high speed Motion Effects with rates greater than 500% no longer play in real time; they now appear in the Timeline as a blue dot effect, and must be rendered. Since any motion effect with a rate greater than 100% plays back inefficiently, and the higher the rate the less efficiently it plays back, real time playback efficiency will improve by rendering such motion effects.
  - **Bug Number:** . (HDV) If a clip contains Timewarp effects, you should render the effects.
  - **Bug Number:** . You might experience effects render issues with stacked effects.

**Workaround:** Render each individual track starting with the bottom track.

- **Bug Number:** UDEV00197962 . When you are working with AVX effects, performing an Expert Render or a Render IN to OUT on a sequence that contains multiple third-party AVX effects might lead to excessive memory consumption that could cause the application to hang or to display errors.

**Workaround:** Render the effects in smaller groups.

- **Bug Number:** UDEV00214545. AVX 1.0 effects might have invalid color levels.
- **Bug Number:** UDEV00194693. You might see problems with superblacks in 16-bit mode.
- **Bug Number:** UDEV00189486. Performing an Add Edit on a promoted Advanced Keyframe Picture-in-Picture effect might cause a “DataPointOneError”.

**Workaround:** Instead of first promoting to 3D, then Advanced Keyframe, promote in the reverse order.

- **Bug Number:** UDEV00132940 . You might see a “FluidMotion Vector Edit Requires Full Resolution” error if you work in FluidMotion™ Vector Edit mode in anything other than full resolution (green mode in the Timeline). Render FluidMotion effects before you combine them with any other effects, especially any other time-based effects.
- **Bug Number:** . (Progressive projects only) If a clip contains any of the following effects, you must render the effects before you apply Scratch Removal:
  - Timewarp effects
  - Any effect that has been promoted to the Advanced Keyframe model
- **Bug Number:** UDEV00134286. Removing or undoing some timewarp effects might cause audio and video to lose sync.
- **Bug Number:** UDEV00161774 . In the Transition Corner Display mode, two of the six frames display incorrect frames during trim operations initiated from the Timeline.

**Workaround:** Trim using the Trim buttons.

- **Bug Number:** UDEV00144549. The Fluid film 2:3 timewarp effect might render incorrectly when you are rendering fluid motion type. The effect might flash a crop of left and right edges.

**Workaround:** Set the left and right mask in the FluidMotion Editor to zero.

- **Bug Number:** UDEV00164929. (HD only) Any animated alpha matte over 35 seconds long might fail.
- **Bug Number:** UDEV00163592. When an Avid effect is applied in an SD 24p progressive project, it can create unwanted aliasing on the resulting clip.

## Effects (Pan & Zoom)

You might encounter the following limitations when you use the Pan & Zoom effect:

- **Bug Number:** UDevC00119611. If you run out of memory when using Pan & Zoom, resize the images to a lower resolution using an application such as PhotoShop.

- **Bug Number:** UDevC00088408. (Macintosh) After the link to a Pan & Zoom effect is broken and you want to reestablish it, the application doesn't prompt you for the source image name in the Open dialog box.  
  
**Workaround:** Import still images into a bin and use them in the edit. With the imported image in the Timeline, apply the Pan & Zoom effect and load the respective file from the Open dialog box. This way you can use "Clip Text" and confirm that the correct images are being loaded.
- **Bug Number:** UDevC00088408. (Macintosh) After the link to a Pan & Zoom effect is broken and you want to reestablish it, the application doesn't prompt you for the source image name in the Open dialog box.
- **Bug Number:** UDevC00081281 . Pan & Zoom keyframe settings can revert to defaults if you select all keyframes when you link to a new picture.
- **Bug Number:** UDevC00025291. When you zoom in with Hi Qual and Ultra Qual filtering, you might experience a system error (Windows) or see green lines when you preview (Macintosh).
- **Bug Number:** UDevC00090139. To improve memory issues, the options in the Pan & Zoom Cache Fast menu are ignored and Video Resolution is used, although when you render the effect, the highest-quality resolution is always used. After you partially render a Pan & Zoom effect, however, you might see a slight pixel shift when you move between the rendered and unrendered portions.

## Export

- **Bug Number:** UDevC00112498. QuickTime Movie export fails when using the Qualcomm PureVoice audio compressor.
- **Bug Number:** UDevC00117134. (Mac Intel) You might have received "image buffer" errors when exporting to DNxHD in After Effects 7. This error does not occur with After Effects CS3 or CS4.
- **Bug Number:** UDevC00106032. (Macintosh) Exporting HDV files to the desktop results in a 0 k file on the desktop. The file will actually appear in your Macintosh User folder. If you export to a folder, note that the file will actually be created one folder level above.
- **Bug Number:** UDevC00090871. (Macintosh) When sending a QuickTime Reference to Sorenson Squeeze, Auto Load and Reveal Files do not work. Squeeze will launch, but the sequence does not load nor are the files revealed in the Finder window.

**Workaround:** Manually import the files into Sorensen Squeeze.

- **Bug Number:** UDevC00098849, 103011. (Macintosh) If you try to Export to a read only drive you may get an exception. Ensure you are exporting to a writable drive.
- **Bug Number:** UDevC00102078, 101999. Export to HDV Device will fail on PC if your sequence contains native HDV media (HDV media captured from tape). Does not apply to Mac systems.

**Workaround:** Transcode to another resolution before performing the export.

- **Bug Number:** UDevC00081152. An error might occur when you export to HDV when the first frame of the sequence is a video mixdown clip.

**Workaround:** Place filler or a frame of non-video mixdown media at the head of the sequence.

- **Bug Number:** UDevC00049124. Currently, our export settings allow a 720x486 size when you export Avid DV, which creates a field alignment issue. Make sure that you set the export settings correctly for 720 x 480 for DV exports. Currently, QuickTime must do a resize from 486 lines down to 480 and you receive an odd interpolation. (Even if you specify 720x486, the Quicktime file displays 720x480.)
- **Bug Number:** UdevC00054456. In NTSC, QuickTime Same as Source and QuickTime Reference clips containing DV material can sometimes show visual distortions when burned to DVD from Avid DVD. This is because the DV portions are resized from the DV raster size 720x480 up to the standard NTSC raster size 720x486.

**Workaround:** When exporting the QuickTime Same as Source or Quicktime Reference clips, choose “Use Avid DV.”

- **Bug Number:** UdevC00007778, UDevC00025957. (Macintosh) The editing application might crash after exporting to an Avid Unity ISIS Read-only workspace. Make sure you export to a Read/Write workspace. You can determine whether a workspace is Read/Write through the Client Manager application. Navigate to the Workspaces tab in Client Manager. The Read/Write workspaces are listed with an R/W under the name of the workspace.
- **Bug Number:** UDevC00078454, UDevC00081066. If you have a mixed-resolution DV 25 sequence and try to export it as QuickTime for DVD using the Apple DV Codec, the .mov might contain artifacts.

**Workaround:** You must use the Avid DV Codec for this kind of sequence.

- **Bug Number:** UDEV00180852. You might receive exception errors when exporting HDV 1080i/59.94 or 1080i 50 as Windows Media.
- **Bug Number:** UDEV00181835. When exporting to an HDV device, at least 4 to 5 seconds of media might be missing from the beginning of the sequence.  
**Workaround:** Add 10 seconds of color bar or black filler at the beginning and at the end of the sequence.
- **Bug Number:** UDEV00140687. When you export a QuickTime Reference movie, do not mix DV and non-DV media. If you mix DV and non-DV media, the resulting movie might contain line shifts.
- **Bug Number:** UDEV00087119. When you export pan automation on an audio clip as AAF, it does not translate in Pro Tools. Pro Tools does not accept varying value pan controls during import.
- **Bug Number:** . In the Export Settings dialog box, the default size is not the image size of the opened project.
- **Bug Number:** UDEV00086337. When you play an exported clip in the Windows Media Player, the sequence stalls in the desktop monitor. The audio plays, the blue bar progresses in the Timeline, and the video and audio output to the client monitor is OK. If the clip that is loaded in Windows Media Player is removed, then the Play operation plays properly in both the desktop and client monitors.
- **Bug Number:** UDEV00138232. Exporting Locators exports only a .txt file with frame count information, not timecode or Feet and Frames. Import also supports only frame count.
- **Bug Number:** . (Encoding to Windows Media) A “Not enough memory is available to complete this operation or WM\_BeginWriting\_FAILED” error results from the application running out of available memory (RAM) while you perform the encode. Encoding to a Windows Media Video codec requires a lot of memory. The amount of memory required is directly related to the number of audio and video profile streams, width, height, bit rate, number of passes, VBR/CBR, and quality of the encoded video, as well as the resolution of the source media. If you encode HD media, you might need to reduce the bit rate, turn on 2-pass encoding, turn on VBR, lower the quality, or reduce the frame dimension.
- **Bug Number:** . A “WM\_FindInputFormat\_FAILED” error might appear if the Windows Media exporter cannot find a suitable input format for a video or audio stream contained in the current Windows Media Export setting's stream profile. For example, using non-standard frame dimensions might result in this error. See the Microsoft Windows Media web site for more detail.

## ICS (International Character Support)

- ▶ **Bug Number:** UDev00089590. Workspace names that contain non-ASCII characters can cause poor performance when working in a bin.  
**Workaround:** Use only ASCII characters in workspace names.
- ▶ **Bug Number:** UDevC00051974. If you capture a clip from a workspace with a French name through CaptureManager™, in the Avid editing application the bin heading Drive might be empty where it should list the French name of the workspace.
- ▶ **Bug Number:** UDevC00051060,UDevC00088815. If you change the font or font size of your input, and see characters rotated 90 degrees, make sure you select the correct font. Do not use any font that begins with the “@” symbol.
- ▶ **Bug Number:** UDevC00052541. Do not create a project using the Euro currency character (ALT 0128). The project fails to be created and a “Can't Open Project” error message is displayed.
- ▶ **Bug Number:** UDevC00022395, 22346. Certain Asian characters might not appear in the correct order in some text boxes in your Avid editing application.

## Import

- ▶ **Bug Number:** UDevC00049653. Occasionally, if you cancel an import of a clip, you might receive a “DISK\_SHARING\_VIOLATION” error.
- ▶ **Bug Number:** UDEV00086727. When you import an uncompressed QuickTime file, a PICT image, or a TIFF image, the first 4 or 5 vertical columns of pixels might truncate when you display the file in the Source, Record, or client monitors.
- ▶ **Bug Number:** UDEV00141372. When you batch import a sequence with a graphic animation that was created in a 30i project and then modified in a 720p project, it might not import.  
**Workaround:** Import the graphic and manually edit it back into your sequence.
- ▶ **Bug Number:** UDEV00138270. Avid editing systems cannot import AVI files created on Avid DS Nitris systems. The import fails with an error message stating that the file format is not supported for import.

## Installation

- **Bug Number:** UDevC00123428. The following applications do not install correctly on Windows Vista 64-bit operating systems:

- Media Composer v3.5, v3.5.1
- Avid Symphony v3.5, v3.5.1
- Avid NewsCutter v7.5, v7.5.1
- Avid MediaLog v25.0.1, v25.0.2
- Interplay Assist v1.6
- Avid Instinct v2.0

The application seems to install correctly but fails to open and displays an error message that corethreads.dll is missing. This occurs because the Path variable does not include the correct location of the Common Files folder.

**Workaround:** After you install the application, edit the system's Path variable with the installation location.

### To edit the Path variable:

1. On the desktop, right-click the Computer icon and select Properties, then click Advanced System Settings.

The System Properties dialog box opens, with the Advanced tab selected.

2. Click the Environment Variables button.
3. In the System Variables section, select Path and click Edit.
4. At the end of the text, add a semicolon (;) and then add the correct location of the Common Files folder. The default path is

```
C:\Program Files (x86)\Common Files\Avid
```

5. Click OK to save the changes and close the Edit System Variable dialog box.
6. Click OK to close the Environment Variables dialog box.
7. Click OK to close the System Properties dialog box.



### Be very careful when you edit the Path variable.

The application should now open correctly.

- **Bug Number:** UDevC00102551. (Macintosh) When launching the editing application, and the Audio is initializing, “CoreMIDIServer.framework” might bounce in the dock. It may remain in the dock until you quit the editing application.

**Workaround:** Delete DigiDioMidDriver.plugin from the Library/Audio/Drivers folder.

- **Bug Number:** UDevC00106344. After installing the editing application on the Vista OS, when you choose to reboot the system, the shutdown cycle is longer than usual.
- **Bug Number:** UDevC00103563. On Windows platforms, occasionally the PACE installers do not properly update the iLok drivers. PACE iLok drivers are used to copy-protect Digidesign plug-ins. If this happens the AudioSuite functionality in MediaComposer will be disabled. To correct the situation the user should uninstall all instances of Interlok Drivers from the Windows Add Remove Control Panel and re-install the Digidesign Drivers from the CD or from Avid > Utilities.
- **Bug Number:** UDevC00103537. Once you install the editing application, and once the editing application tries to launch, while it is initializing, you might receive an “Unable to create index for editor slides” error message.

**Workaround:** Right click the product.exe and choose “Run as administrator.” This causes the mdb and pmr files to update in the Avid\_MediaFiles folder. The executable is located (by default) in C:\Program Files\Avid\Avid Product Name.

- **Bug Number:** UDevC00103474. (Vista) When the editing application is launched and a firmware update is required, you might be prompted to relaunch using 'Run As Administrator'. To run as administrator, right click the product.exe and select Run as administrator. The executable is located (by default) in C:\Program Files\Avid\Avid Product Name. Run as administrator is not available by right-clicking in the Avid editing application Shortcut icon.

## Interplay Workgroup

- **Bug Number:** UDevC00105773. When you create a video or audio mixdown and add a locator, you might receive an “Exception: CM\_NO\_TC” error when you try and check the clip in to Avid Interplay. If you add the locator in Assist, then go back to the editing application and perform an Update from Interplay on the clip, the clip will check in successfully.
- **Bug Number:** UDevC00105408. (Vista) If you have a P2 drive mounted and you try to open the Interplay Service Configuration tool, you might receive an Exception error. Clicking through the error message might allow you to open the tool. If you unmount the P2 drive, the tool will open.

- **Bug Number:** . When checking out a complex or long sequence from an Avid Interplay environment the following message might appear: “A request for data from the asset manager is taking a long time to complete. Would you like to continue waiting for the operation to complete or would you like to cancel?” If you choose to wait the sequence may load or you may get this message multiple times until the check out actually occurs.
- **Bug Number:** UDevC00093257. You might receive an access violation error while dragging multiple clips from the Interplay window into a bin. This occurs if you select an individual clip, drag it to the bin and then repeat the process quickly.

**Workaround:** Select multiple clips and drag them to the bin.

- **Bug Number:** UDevC00091228. Selecting Check In All Open Bins from the Fast menu (hamburger menu) in the bin might not check in the open bins.

**Workaround:** To check in all open bins, select Check In All Open Bins from the File menu.

- **Bug Number:** UDevC00090338. After you perform a search for media in the Interplay Window, you cannot refresh the search results displayed in the Research panel by pressing F5. If you want to refresh the results, repeat the search.
- **Bug Number:** UDEV00052480. Batch Import of files containing Alpha. This problem occurs if you want to batch import files in SD and HD formats and then use Dynamic Relink to switch between the different formats. The problem occurs with QuickTime movies, graphics, and sequences that contain alpha. You can batch import the files and relink to the different formats, but if you exit and then restart the Avid editing application you can no longer relink to the HD format. The system displays an “Exception: NO Compressed Data Format found” error message.

**Workaround:** You cannot use Dynamic Relink with HD and SD clips that contain alpha. Import the HD files with alpha as individual clips. When you want to switch to HD format, edit the HD versions into your sequence.

- **Bug Number:** UDEV00227044. If you import a graphic from your local drive into a project in an Avid editing application, change the original name of the clip to a name of your choice, and check that clip into a folder in the Interplay Window, the new name does not appear in the Interplay Window even when you refresh the window. You see only the original name.
- **Bug Number:** UDEV00226957. When you import a clip onto local storage into a local bin and then delete the clip’s media, you continue to see the clip in the Avid editing application Source monitor instead of the message “Media Offline.” If you try to play the clip, an error message box opens.

**Workaround:** Open another clip in the Source monitor, and then reopen the clip with the deleted media to correctly see the “Media Offline” message.

- **Bug Number:** UDEV00226657. When you incorporate clips and subclips that include locators added in Interplay Assist into a story in Instinct, the locators do not appear in the story. If you open the same story (sequence) in an Avid editing application, the locators do not appear there, either.
- **Bug Number:** UDEV00217606. In the Avid editing application, the Record Track monitor buttons might be deselected if the following happens:
  1. On System 1, you create a sequence and check it into a folder in the Interplay Window.
  2. On System2, you check out the sequence and load it into the Timeline.
  3. On system1, you edit the sequence and check it into the Interplay folder again.
  4. On system2, you refresh the Interplay window then check out the same sequence again.

**Workaround:** Select the Record Track buttons again.

- **Bug Number:** UDEV00299154 . In an Avid editing application, if you have a sequence that you have not checked into the Interplay Window and you try to use the Transfer > Send to Workgroup command, you might experience an error.

**Workaround:** Check the sequence into the Interplay Window before you attempt to transfer it.

- **Bug Number:** UDEV213923 . In workgroup environments prior to Avid Interplay, you could automatically consolidate from NewsCutter during Send to DMS. With the Avid Interplay release, the automated consolidate is not available. Choose to consolidate prior to sending to DMS.
- **Bug Number:** UdevC0055755. When working with MultiRez, high-quality audio cannot be distinguished from up-sampled proxy audio created with previous versions of the editor. For instance, an 8 kHz proxy audio up-sampled to 48 kHz on import in Interplay version 1.0 is considered as good as a real 48 kHz high quality audio. In that case, if MultiRez is set to use 48 kHz audio, it picks up the most recent file of the two.

## Force Disconnect Client Mode in an Interplay Environment

Your system administrator might need to temporarily remove your editing system from access to the network. This might occur if new software needs to be installed or if components need to be updated, for example. To force a disconnect, your administrator runs

a script that forces disconnection from the network without physically removing your system. Your administrator can also reconnect your system at the appropriate time using another script.

It is possible to import from shared drives and export to them in Forced Disconnected Client mode. Avid recommends, however, that you do not import from or export to shared drives when your administrator has force-disconnected your editing system. Avid does not support any workflow that includes importing from or exporting to shared drives when the system is in Forced Disconnected Client mode.

In general, if you are in Forced Disconnected Client mode and if you import or export using shared drives, after the import or export those drives might appear to be available for other purposes such as importing, capturing, playing, or deleting media, but they are not available. Similarly, options for shared storage might appear to be available in various settings dialog boxes and shared drives and media might appear in various menus, tools, and applications; Avid does not support use of these settings, drives, or media.

To remove the shared drives from your drive lists, disconnect your network cables as described in “Voluntarily Disconnecting from the Interplay Environment” in the Help, or exit your editing application and restart it.

The following limitations describe specific instances of drives and options appearing in Forced Disconnected Client mode:

- **Bug Number:** UDevC00083319 . In the Select Project dialog box, shared workspaces and projects are available and should not be.
- **Bug Number:** UDevC00083320,UDevC00083772. Shared drives and media are available in the Media tool and in the MetaSync™ application and should not be.
- **Bug Number:** UDevC00083321. In the Interplay Server Settings dialog box, you can change the Interplay server name and you should not be able to
- **Bug Number:** UDevC00083371 . In the Capture tool, you can select the Interplay Folders option as your capture destination and you should not be able to.
- **Bug Number:** UDevC00083374. In the MXF Media Files tab of the Capture Settings dialog box, you can select the “During capture, clip is updated in Interplay” option and you should not be able to.
- **Bug Number:** UDevC00083477. In the Temporary File Directory option of the General Settings dialog box, you can type the name and location of a shared drive and you should not be able to.

- **Bug Number:** UDevC00083409. Shared drives and media are visible in the Hardware tool and should not be.
- **Bug Number:** UDevC00083740. Shared drives are visible in the Import dialog box and should not be.
- **Bug Number:** UDevC00083826. Options in the Media Services Settings dialog box are available and should not be.
- **Bug Number:** UDevC00083496. Options in the Transfer Settings dialog box are available and should not be.
- **Bug Number:** UDevC00084455, 84773. Selecting LANshare, PortServer settings, or ProEncode™ appears to be available but should not be. Do not select these options.
- **Bug Number:** UDevC00084446. Dynamic Relink can be enabled but that should not have been allowed. Do not enable it.
- **Bug Number:** UDevC00084600, 84844. With several of the options in the File menu, you are allowed to select a shared workspace as a destination but you should not be able to. Do not select a shared workspace in this context.
- **Bug Number:** UDevC00084610. If you select Automatic Login at Project Selection in the Interplay User Settings dialog box, enter Disconnected Client mode, exit the mode and the editing application, reconnect, and then restart the editing application, you need to log into Interplay again and you shouldn't have to.
- **Bug Number:** UDevC00088542. In Forced Disconnect mode, if you make a change to your User settings, the change might appear for all other users, as well.

## JVC

- **Bug Number:** UDevC00106545. JVC recommends using the BR-HD50 deck to capture and batch-capture HDV media recorded with JVC cameras.
- **Bug Number:** 106030. The JVC GY-HD250U camera might drift out of sync while shooting in 720p/59.94. To avoid this issue, turn on the camera in 720p 23.976 and then switch the format to 720p 59.94 causing a soft reboot.
- **Bug Number:** UDevC00106380. The Imported M2T files that were captured with a JVC GY-HD250U camera via the FireStore DR-HD100 will show up in the bin with the wrong durations. This occurs in 720p 50 and 720p 60 projects.

- **Bug Number:** UDevC00106401. Currently, captured or imported M2T files might contain 1/2 frame offset. This occurs in 720p 29 and 720p 25 projects.

## Locators

- **Bug Number:** UDevC00080303. If you add a locator to a shotlist, and then open the sequence in an editing application, the locator appears, but if you perform a match frame on the locator, it might not appear in the master clip.

**Workaround:** In the editing application, check the master clip in question out of Interplay and then update the bin or the clip. The locator appears.

- **Bug Number:** . A new item has been added to the Fast menu in the Locators window. “Disable Locator Popup” disables the locator pop-up window. It is disabled only for the work session. When you restart the Avid application, the locator pop-up menu is enabled.
- **Bug Number:** UDevC00079172. (Macintosh) When you export locators from the Locator tool, the file might not be saved with the correct .txt extension and you might not be able to import it.

**Workaround:** In the Choose Location for Exported Locators dialog box, add the file name extension .txt to the end of the file name before you click Save, or add the extension to the saved file before you import it.

## Panasonic P2

- **Bug Number:** UDevC00101216. Reveal File does not function on master clips linked from P2 cards or virtual volumes.
- **Bug Number:** UDevC00098594, UDevC00097992. Panasonic P2 writeback is not supported on the Macintosh platform.
- **Bug Number:** . Export to P2 limitations:
  - Use Marks and Use Enabled tracks are ignored on export.
  - All Audio must be PCM 16b/48K.
  - All audio tracks will be exported, although P2 devices either support 2 or 4 audio tracks. Therefore sequences should be built for delivery to the specified P2 playback device. Sequences with 6 audio tracks will have 6 audio tracks and the P2 device will only playback the first 2 or 4 tracks.
- **Bug Number:** . Importing P2 limitations (Macintosh):

- Importing P2 Clips in a bin is only supported with one P2 Card mounted. With two or more P2 cards mounted, use the Media Tool, select the P2 Drives, click All Projects and click OK. All Master Clips from the P2 cards will appear in the Media Tool. Drag them to a bin.
- When importing from the Panasonic P2 Store device, Media Tool must be used as well on Macintosh.

- **Bug Number:** . SD/HD Mixed sequences are not supported.
- **Bug Number:** . 1:1 MXF media cannot be exported in both SD and HD projects. Transcode 1:1 MXF before exporting.
- **Bug Number:** . (Macintosh) Hotswapping P2 cards with the editor launched is currently not supported.
- **Bug Number:** UDevV00090107. Occasionally the File > Import P2 > Media command does not consolidate media to the drives.

**Workaround:** Close and re-open the bin and then execute the command again.

- **Bug Number:** UDevC0056503. When you view a P2 clip that spans across multiple P2 cards in the timeline, you might be surprised as to what you see and don't see due to the history of mounting P2 cards on your current system and the P2 cards that are currently mounted. Be aware that even though media is offline, or you are not able to view the P2 media in the Timeline, the media is not lost. The media appears when the card containing it is mounted.
- **Bug Number:** 00080719. If you have P2 clips on a P2 card and you display the clips in the Media tool, you might be able to delete the audio and video .mxf files from the Media tool.
- **Bug Number:** UdevC00058135. If you remove a card from a slot in the P2 reader and do not put another card in the reader, you must delete the P2 folder before inserting that same card in another slot.
- **Bug Number:** UdevC00058133. A DVD drive cannot be a media drive. If a CONTENTS folder is located on the root level of the DVD, you might see a “No clips were found” message when performing an Import P2 Clips to Bin.

**Workaround:** Create a folder that contains the CONTENTS folder on the DVD. This instructs the editor to mount a virtual drive.

- **Bug Number:** UDevC00051731. When the P2 CONTENTS folder is located at the root level on a drive where the Avid editing application looks for media files, you might encounter errors when importing P2 clips. For example, if you are working on a laptop, the Avid editing application and local storage folders are on the same drive and are usually located at the root level. If you create virtual P2 volumes on the Desktop, you might encounter a “No clips were found” message when trying to import the P2 clips and media.

**Workaround:** If you locate the virtual P2 volume in a different location such as a subfolder on the Desktop, you should be able use virtual P2 volumes.

- **Bug Number:** . If you experience unusually long scan times, check to make sure both the local time and Greenwich Mean Time (GMT) are set correctly on your camera. If the GMT is not set correctly, you may need updated firmware for your camera.
- **Bug Number:** . Play performance for a multi-stream sequence suffers when you directly access media from the P2 media cards in the AJ-SPX800P camera.
- **Bug Number:** UDEV00163029. If you turn off the P2 card reader while a bin accessing P2 media is open, attempting to load any P2 clip results in a DISK\_FILE\_NOT\_FOUND message in the Source monitor window. The message should read Media Offline.
- **Bug Number:** UDEV00163032. Dupe detection is not available for P2 source material.
- **Bug Number:** . The following limitations currently apply when working with AVC-Intra resolutions:
  - Real-time playback support on Avid Symphony Nitris is not guaranteed.
  - QuickTime export is not supported.
- **Bug Number:** UDevC00116685. You cannot export a QuickTime movie using the Same as Source option with AVC-Intra material. ProEncode does not work with AVC-Intra material. This is related to the QuickTime problem because ProEncode creates a QuickTime Reference movie as part of its process.

## Play

- **Bug Number:** UDevC00117308. You might experience dropped frames when playing back XDCAM media with effects. When playing back media, a number of variables affect play performance; such as your CPU power, GPU power, sequence complexity and the raster settings.

- **Bug Number:** UDevC00109242. (MacBook Pro) After an initial launch of the editing application when attached to a Mojo, you might receive an “Assertion failed” error when playing back an HD sequence.

**Workaround:** Switch the project to NTSC or PAL.

- **Bug Number:** UDevC00101060. You might experience a slight delay at the start of play when Output to DV Device is enabled with progressive projects.
- **Bug Number:** UDevC00117987. It is possible on certain slower machines, when playing in MultiCamera mode, you might notice one or more cameras or the line-cut stutter a few seconds into the sequence. This happens most often when displaying the MultiCamera composite or line-cut to the client monitor on these older, slower systems. To help improve performance, Avid has provided a console command which allows you to pre-render more frames. This will slow down the start of play, but improve the overall playback performance. To increase the number of pre-render frames:

**Perform the following:**

1. Open the Console window by selecting Tools > Console.
  2. In the Console command line, type the following command followed by the number of frames you want to prerender:  
`multicampreload 20`
  3. Press Enter (Windows) or Return (Macintosh). The value is saved. You do not need to reenter the command when you relaunch the editing application. To restore the default value, enter the command with no value.
- **Bug Number:** UDevC0088738. When you scrub a clip with “Fast Scrub” on, you might notice that when you stop scrubbing, the video may continue to play in the record monitor. This might be more noticeable in HD projects or when you are working on shared storage. Fast scrub actually has a number of frames in flight while you drag the blue bar. The in process frames continue to play once you stop scrubbing.
  - **Bug Number:** UDevC00103865. (Mojo DX) Currently, if you open a 24p PAL, 25p PAL or 720p 50 project and load a clip into the timeline and then play the clip, you may see frames drop.

**Workaround:** Set your project to an HD project type and then back to your 24p or 25p project. You only have to do this once per session.

- **Bug Number:** UDevC00026088. When you play media and then you press stop, the source monitor stops, but the external client monitor steps back approximately 2 frames.

- **Bug Number:** . (Macintosh) QuickTime reference movies are useful as long as you are working with Avid media files available on your local system or in an Avid Unity environment. However, if you expect to move the exported QuickTime file to a system that doesn't have access to the media, then you should use the standard QuickTime export so the media files and QuickTime wrapper can be moved as one file.
- **Bug Number:** Udev00209633. With Full Screen Playback enabled on a single monitor, the video might stutter and you might notice tearing toward the top of the image during playback. Tearing might also appear if you use variable-speed play.
- **Bug Number:** . When the Avid editing application stops streaming play, a number of additional frames are sent to the DNA device in order to keep the client monitor synchronous with the desktop display. The DNA device must play out that number of frames after the desktop has stopped playing. To make sure you view the actual last frame, the application then snaps the client monitor back to the frame on the desktop. This might be more apparent when playing HD media.
- **Bug Number:** . If you do not see video output to your device, make sure that the appropriate device is selected in the Special > Device menu. If FireWire is selected in the Device menu, make sure Output to Device is selected in the Video Display Settings.
- **Bug Number:** Udev00141002. If you experience a flashing monitor when attempting to play using the Japanese version of Windows XP, and your monitor does not appear to be covered by anything, adjust the state of your Language bar by maximizing and minimizing it. This restores the ability to play.
- **Bug Number:** . (Adrenaline) LTC output is now off by default. To turn it on, open General Settings and enable “Generate LTC On Playback”.

## Projects

- **Bug Number:** UDevC00100476. The following project types do not support XDCAM or HDV raster types:
  - 1080p 23.976
  - 1080p 25

The only raster type available for these formats is Standard.
- **Bug Number:** UdevC00025426. (Windows Only) Avid Attic folders can only be created by Administrators. An Administrator has to first launch the application, open a project, close the project and quit the application. Then when a non-Administrator user uses the application, their work is saved to the Avid Attic.

- **Bug Number:** UDevC00099790. You should note the following when transcoding media. If you have a project in one format, such as 1080i 50 and you add a supported progressive format to the clip such as 1080p 25, once you transcode the media, if you try to delete the clip, the clip contains both progressive and interlaced media. The delete dialog does not indicate that the clip you are trying to delete contains both progressive and interlaced media.
- **Bug Number:** UDevC00025979. For NewsCutter projects, you can only select base timecode (TC1) display formats in the Tracking Information menu. You can view other timecode formats in the Timeline window, but tracking information does not display above the Source/Record monitor except for the base timecode.

## Settings

- **Bug Number:** UdevC00989750. If you take your user settings from your Adrenaline, Mojo or Software Only system forward to a system running with a Nitris DX, Fast scrub will be disabled. New user settings with a system running with a Nitris DX will have Fast Scrub enabled by default.
- **Bug Number:** UDevC00100486 . Currently, when saving toolsets, the bin position is not saved.
- **Bug Number:** . Do not carry User Profiles from a previous version to this version. Create new user settings. If you do use previous settings, the size of tools and windows might not be as expected, especially tools and windows that have been updated for this version.

## Titles

- **Bug Number:** 0107356. (Macintosh) You might see vertical gray lines when you horizontally scroll the pages of a crawling title in Title Tool.
- **Bug Number:** UDevC00107065. (Macintosh) The background image might not display when editing an existing title from the Timeline.  
**Workaround:** Either promote the title to Marquee, or modify the existing title from the bin.
- **Bug Number:** 106910. (Adrenaline) Currently, an image might appear distorted in the Title Tool if you are in Draft or Best Performance play back mode.  
**Workaround:** View the image in the Title Tool in Full Quality or Full Quality 10-bit mode.
- **Bug Number:** UDevC00054752. If you re-create a rolling or crawling title in your sequence, the Scroll Position parameter values for the first and last keyframes are not preserved. They are set to the default values (start and end).

**Workaround:** Promote the title to advanced keyframe model before you re-create.

- **Bug Number:** UDevC00047857. (Macintosh only) If you select the classic Title tool eyedropper and then quit the Avid application, the application hangs.

**Workaround:** Deselect the Title tool eyedropper before you exit the Avid application.

- **Bug Number:** UDevC00080610. Avid suggests that you do not attempt to edit the nested tracks of a re-created rolling or crawling title. If you attempt to select or edit one of these types of nested tracks, an error occurs. This is also the case with a re-created static title on its alpha channel subtrack.

- **Bug Number:** UDevC00080134. A sys\_error occurs when you modify a title to an available drive with Render settings that are set to an unavailable drive (a drive that you do not have write access to). A .bak file of the title also appears in the bin.

**Workaround:** Close the Title tool and change the Render settings to a drive that you do have write access to.

- **Bug Number:** UDEV00218429. Character spacing might be inaccurate in Title Tool titles using large font sizes. Some character pairs might appear too close together, or overlapping. In HD projects, the problem is only visible in the rendered title clip in the bin. In SD projects, the problem is visible immediately in the Title Tool. Also, once the problem has occurred in text using a large font size, it might persist when you create other text objects in the title at any font size.

**Workaround:** The best general workaround is to promote the title to Marquee®. Text in Marquee titles does not have the same problem at large font sizes. Also, if you do not need your final text to use a large font size, avoid converting it to a large font size at any point in your workflow, or retype it as a new text object at a smaller size if increasing the font size causes the problem.

- **Bug Number:** UDEV00218032. Marquee title format does not need to change in normal workflows. In most normal workflows, the title format in Marquee automatically matches the project format in your Avid editing application and you do not need to change it. If you change the title format in Marquee so that it does not match the project format in your editing application, you might see artifacts around the edges of some title objects. One situation in which you might need to change the Marquee title format occurs when you are creating a title by opening an existing .mqp file. If the .mqp file's format does not match the project format in your Avid editing application, you should change the title's format to match the project format in your editing application. For more information on changing the title format, see "Changing Title Formats" in the Marquee Help.

- **Bug Number:** UDEV00221549. When you render a rolling or crawling NTSC SD title with Same as Source selected in the Media Creation dialog box in an HD project, you might see problems with the title.

**Workaround:** For highest quality titles, re-create your title media in the format of the project in which you are working; in this case, re-create your SD title media in an HD format.

- **Bug Number:** UDEV00189160. Unrendered back-to-back titles in a 1080i HDV sequence might not play in real time. The second title does not display.

**Workaround:** Render the titles.

- **Bug Number:** UDEV00162337. Rolling and crawling titles in 24p and 25p projects might display a “Layout Mismatch” error when in Full Quality mode.

**Workaround:** Select another quality mode. The error also goes away if you toggle to the HD project equivalent and load the title.

- **Bug Number:** UDEV00163549. When you reedit a Marquee title in the Timeline, you might see artifacts in the video background. This is cosmetic only and does not appear in the resulting title.

**Workaround:** If you reedit the title in the bin rather than the Timeline, the artifacts do not appear.

- **Bug Number:** UDEV00163010. For projects whose formats are changed to HD, if there are Marquee crawls in sequences, these need to be modified to keep them as Avid DSK titles. Redit these titles by using the effect editor to bring up Marquee. If when saving to a bin in Marquee you receive a message that the title is animated or that it cannot be saved directly to the Timeline, then perform the following workaround.

**Workaround:** Select the Crawl text box. Press the “C” toolbar button within Marquee to cause the crawling text box to extend for the new larger width of the title. Now you should be able to save to the bin or the Timeline as before and the title will not be animated.

- **Bug Number:** UDEV00161170 . Page breaks appear on rolling and crawling titles when an HD title is over SD media, or an SD title is over HD media.

**Workaround:** Recreate the title at the same resolution as the underlying video.

- **Bug Number:** UDEV00136646/UDEV00136165. HD titles appear aliased when you are not in Effect mode. Some titles you create in HD projects might look aliased (blocky) when you view them at Full Quality in Source/Record mode. To improve the visible quality, render the title or view it in Effect mode.
- **Bug Number:** UDEV00134561. The application might appear frozen after you edit a Marquee title in the Timeline. If you edit a Marquee title that is already part of a sequence in the Timeline and then exit Marquee, you might not be able to perform any other operations.

**Workaround:** Press the Escape key. Use a different user setting to avoid the problem.

- **Bug Number:** UDEV00138188. Rolling titles created in SD and rendered in HD display 1 line at the top of the matte when they are rendered.

**Workaround:** Recreate the title and matte before you render.

- **Bug Number:** UDEV00135729. If you change the size of text, it might yield different kerning results. If you highlight text and change the text properties, the kerning result might be different than if you had changed the text properties in the Parent text box. For consistent results, change the text properties in the Parent text box.

- **Bug Number:** UDEV00140546, and UDEV00140564. When you edit large or unrendered SD crawling or rolling titles in an HD project, switch to SD, promote the title to Marquee, save the title in SD, then open the title in HD.

This workaround is not possible for a 720p project, but you can open the 720p bin in a 30i project and modify the title there, as long as there is an SD version of the sequence.

- **Bug Number:** UDEV00139482. Titles created in 4x3 SD and then re-created in 16x9 (SD or HD) appear to shift to the left. You must manually reedit the title in 16x9 for correct positioning.

**Workaround:** In 16x9 mode, load the original 4x3 title in the Title tool. Click the Selection tool, select Edit > Select All, and then click Object-Group. Click Alignment > Center in Frame Horiz. Save the title to the bin.

- **Bug Number:** UDEV00141084. You might receive an “Out of Range” error when you try to modify and then re-create rolling and crawling titles in the timeline in a 720p project.

**Workaround:** Manually reedit the titles into the sequence.

## XDCAM

- **Bug Number:** UDevC00120079. If you are working with the PDW U1 device and you have "Automatically Import Proxies when disk is inserted" selected in the XDCAM Import Settings window, you will not receive the automatic prompt to import the proxy clips when the disk is inserted. For this device, you must manually import the proxy clips. The high resolution batch import process has not changed.
- **Bug Number:** UdevC00121377. (XDCAM writeback) If you export a 720p50 or 720p59 sequence with an odd number of frames, you will receive a message indicating the sequence needs an even number of frames to export successfully. Add or subtract a frame and perform the export again.
- **Bug Number:** UDevC00117308. You might experience dropped frames when playing back XDCAM media with effects. When playing back media, a number of variables affect play performance; such as your CPU power, GPU power, sequence complexity and the raster settings. Depending on the complexity of your sequence, you might need to render some effects if you want to preview them in real time and at full quality, or before you can output a finished sequence.
- **Bug Number:** UDevC00116558. When you batch import XDCAM clips from a virtual volume, the system re-imports the proxy media into your bin. If you batch import XDCAM clips directly from the XDCAM disk, this works as intended. If you do not have access to the XDCAM disk, Avid recommends that you import the hi-res XDCAM media when you import from a virtual volume and then edit your sequence.
- **Bug Number:** . When you import XDCAM files, be aware that Avid does not support the batch import workflow when you are working in the following Sony XDCAM camera modes: Picture Cache Record Mode, Interval Record Mode, or VFR (Variable Frame Rate) Mode (UCC/OCC - Undercrank/Overcrank). An error message appears which informs you that the video is not supported. However, the High-Rez versions of these clips can be imported. Their timecode values, however, will be inaccurate. The Avid editor appends its own generic timecode to clips recorded in any of the previously mentioned modes.
- **Bug Number:** UdevC00164589. XDCAM proxy media **will not** export to a QuickTime reference movie. This is a limitation for all Long-GOP media types.

If you export as a regular QuickTime movie, MPEG 4, or as Windows Media 9, the export is successful. Or, you can transcode the proxy sequence to DV 25 or MPEG-IMX and then export as QuickTime reference.

**Workaround:** Import the whole XDCAM HD clip and then transcode it.

- **Bug Number:** UdevC00078552. The Avid editing applications refer to XDCAM HD 25 Mb/s media files as HDV 1080i 50/60. These Dynamic Relink settings are only available in project types 1080i/59.94 HDV or 1080i/50 HDV.

## Extending Your Usable Address Space and Adding RAM for Improved Performance (Windows)

The Microsoft Windows XP and Vista 32-bit operating systems limit every program to 2 gigabytes (GB) of address space. It reserves the remaining 2 gigabytes of address space for its own use. The operating system includes a boot-time mechanism that allows applications access to a larger virtual address space than was previously available. Avid provides a utility for setting the boot-time mechanism to extend the process address space.

For Microsoft Windows XP and Vista 64-bit operating systems, applications are allocated an address space well beyond the 2-gigabyte limit allocated by the 32-bit operating systems. No utility is needed to tell the 64-bit operating systems to allocate additional memory for the applications.

Setting your Avid editing system to access a larger virtual address space might improve working with HD projects without running out of memory. Even though you might gain more memory space, this can be quickly consumed with bins and complex HD effects. For best performance, if you choose to extend your address space beyond 2 gigabytes, you should install an additional 1 or 2 GB of RAM.

### Using Install3GB.exe to Extend Your Usable Address Space

It is not necessary to run this executable on Vista 64 systems. Perform this procedure on Vista 32 systems or Windows XP systems.

#### To extend the application address space:

1. Double click the Install3GB.exe file in the Utilities\3G folder where the Avid application is installed.

A window opens. You must have administrative privileges to run this utility.



*The hardware and software configuration you are running, Nitris DX, Nitris, Adrenaline, and so on, determines the amount of memory you should allocate for the application address space.*

2. Type the amount of memory you want to allocate for the application space at the prompt. The recommended settings are:
  - 2700 for Mojo and Adrenaline

- 2700 for Mojo DX and Nitris DX
- 2500 for Symphony Nitris Classic
- 2700 for Software Only systems

Install3GB updates the current configuration you are running; it does not create another one.

After pressing any key the window closes and you will need to reboot the computer.

## Restoring the Original Configuration

You can restore the system to the original configuration.

### To restore the configuration:

1. Run the Install3GB.exe as described in [“Using Install3GB.exe to Extend Your Usable Address Space” on page 61](#).
2. Type 0 (zero) for the memory setting.  
This removes the “userva” setting in the boot configuration.
3. Reboot the system.

## Documentation Changes

The following change has occurred since the print documentation was completed.

### Exporting to XDCAM

In the Avid editor Help, the topic: “Exporting to XDCAM,” step 8 informs you that “If your exported sequence has more than two audio tracks, only two tracks are exported, even though the Sony XDCAM device is capable of handling 4 to 8 tracks. If your sequence has more than two tracks, they are mixed down during export.”

This should now read: “If you are using the Sony PDW HD1500 or the Sony PDW 1500 XDCAM devices, export of up to 8 tracks of audio is supported for the MPEG IMX and XDCAM HD 50 Mbits formats. For other formats or devices that do not support 8 tracks, the system mixes down to audio tracks 1 and 2 during export.”

### Capturing DV 25 Media

In the “Capturing DV 25 Media” topic in the help, the following paragraph was unintentionally omitted.

- If you are using an Avid Nitris DX or Mojo DX, or if you are not using an Avid input/output hardware device (software-only), you use a 1394 port on your computer (Host 1394). You specify that you are capturing via the 1394 port by selecting Host 1394 from the Video menu in the Capture tool.

## Selecting a DV Device

In the “Selecting a DV Device” topic in the help, the following paragraph was unintentionally omitted.

- If your system has an Avid Nitris DX or Avid Mojo DX attached, the DNA/1394 button and the Special > Device menu do not appear in the user interface. DV capture through 1394 and non-DV capture through your input/output hardware operate independently. You specify that you are capturing via 1394 by selecting Host 1394 from the Video menu in the Capture tool.

## Selecting Asset Types

You should ignore the topic “Setting the Interplay Window Display” in the Help and use the following procedure. The option to select which media types display in the Interplay Window has been moved from the Bin menu to the Interplay Window.


### To select asset types and reference clips to display:

1. Right-click the Type column heading in the Research panel and select Set Type Filter.



*You need to right-click the column heading. If you right-click elsewhere in the column, the option does not appear in the context menu.*

The Set Type Filter dialog box opens.



2. Select the asset types you want to display.
3. (Option) Select “Show reference clips” to display objects that are referenced by sequences.
4. Click OK.
5. (Option) Save the layout if you want to preserve your type filter settings.

## Importing Proxy Media

Avid's new feature “Avid Media Access (AMA)” allows you to link directly to P2, XDCAM, or XDCAM EX media. However, if you want to import XDCAM proxy media, you can do the following.

### Turn off AMA:

1. In the Project window, click the Settings tab.
2. Double-click AMA.  
The AMA Settings dialog box appears.
3. Click the Volume Mounting tab.
4. Deselect “Enable AMA Volume Management.”
5. Quit and restart the Avid application.
6. Follow the steps in the Help topic: “Importing Proxy Media from an XDCAM Disc.”

For more information about AMA and Importing and Exporting, see the section on “File Based Media” in the Help or in the Advanced Guide .pdf of your Avid editing system.

# Legal Notices

Product specifications are subject to change without notice and do not represent a commitment on the part of Avid Technology, Inc.

The software described in this document is furnished under a license agreement. You can obtain a copy of that license by visiting Avid's Web site at [www.avid.com](http://www.avid.com). The terms of that license are also available in the product in the same directory as the software. The software may not be reverse assembled and may be used or copied only in accordance with the terms of the license agreement. It is against the law to copy the software on any medium except as specifically allowed in the license agreement.

Avid products or portions thereof are protected by one or more of the following United States Patents: 4,746,994; 4,970,663; 5,045,940; 5,267,351; 5,309,528; 5,355,450; 5,396,594; 5,440,348; 5,452,378; 5,467,288; 5,513,375; 5,528,310; 5,557,423; 5,577,190; 5,583,496; 5,584,006; 5,627,765; 5,640,601; 5,644,364; 5,654,737; 5,715,018; 5,719,570; 5,724,605; 5,726,717; 5,729,673; 5,745,637; 5,752,029; 5,754,851; 5,799,150; 5,812,216; 5,828,678; 5,842,014; 5,852,435; 5,999,406; 6,038,573; 6,061,758; 6,141,007; 6,211,869; 6,532,043; 6,546,190; 6,596,031; 6,636,869; 6,747,705; 6,763,523; 6,766,357; 6,813,622; 6,847,373; 7,081,900; D352,278; D372,478; D373,778; D392,267; D392,268; D392,269; D395,291; D396,853; D398,912. Other patents are pending.

No part of this document may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, for any purpose without the express written permission of Avid Technology, Inc.

Copyright © 2009 Avid Technology, Inc. and its licensors. All rights reserved.

## Attn. Government User(s). Restricted Rights Legend

U.S. GOVERNMENT RESTRICTED RIGHTS. This Software and its documentation are "commercial computer software" or "commercial computer software documentation." In the event that such Software or documentation is acquired by or on behalf of a unit or agency of the U.S. Government, all rights with respect to this Software and documentation are subject to the terms of the License Agreement, pursuant to FAR §12.212(a) and/or DFARS §227.7202-1(a), as applicable.

## Trademarks

888 I/O, Adrenaline, AirPlay, AirSPACE, AirSPACE HD, AirSpeed, ALEX, AniMatte, AudioSuite, AudioVision, AutoSync, Avid, Avid Advanced Response, Avid DNA, Avid DNxcel, Avid DNxHD, AVIDdrive, AVIDdrive Towers, Avid DS Assist Station, Avid ISIS, Avid Learning Excelsior, Avid Liquid, Avid Mojo, AvidNet, AvidNetwork, Avid Remote Response, AVIDstripe, Avid Unity, Avid Unity ISIS, Avid Xpress, AVoption, AVX, CamCutter, ChromaCurve, ChromaWheel, DAE, Dazzle, Deko, DekoCast, D-Fi, D-fx, DigiDelivery, Digidesign, Digidesign Audio Engine, Digidesign Intelligent Noise Reduction, DigiDrive, Digital Nonlinear Accelerator, DigiTranslator, DINR, DNxchange, do more, D-Verb, Equinox, ExpertRender, FASTBREAK, Fast Track, FieldPak, Film Composer, FilmScribe, FluidMotion, FXDeko, HIIIP, HyperSPACE, HyperSPACE HDCAM, IllusionFX, Image Independence, iNEWS, iNEWS ControlAir, Instinct, Interplay, Intraframe, iS9, iS18, iS23, iS36, IsoSync, LaunchPad, Lightning, Lo-Fi, Magic Mask, make manage move | media, Marquee, Maxim, MCXpress, Media Browse, Media Composer, MediaDock, MediaDock Shuttle, Media Fusion, Media Illusion, MediaLog, Media Reader, Media Recorder, MEDIArray, MediaShare, MediaStream, Meridien, MetaFuze, MetaSync, MicroTrack, MissionControl, NaturalMatch, Nearchive, NetReview, NewsCutter, Nitris, OMF, OMF Interchange, OMM, Open Media Framework, Open Media Management, PCTV, Pinnacle MediaSuite, Pinnacle Studio, Pinnacle Systems, ProEncode, Pro Tools, QuietDrive, Recti-Fi, RetroLoop, rS9, rS18, Sci-Fi, ScriptSync, SecureProductionEnvironment, Show Center, Sound Designer II, SPACE, SPACEShift, SpectraGraph, SpectraMatte, SteadyGlide, Symphony, TARGA, Thunder, Thunder Station, TIMELINER, Trilligent, UnityRAID, Vari-Fi, Video RAID, Video Slave Driver, VideoSPACE, Xdeck, and X-Session are either registered trademarks or trademarks of Avid Technology, Inc. in the United States and/or other countries.

Adobe and Photoshop are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States and/or other countries. Apple and Macintosh are trademarks of Apple Computer, Inc., registered in the U.S. and other countries. Windows is either a registered trademark or trademark of Microsoft Corporation in the United States and/or other countries. All other trademarks contained herein are the property of their respective owners.

Avid Media Composer ReadMe • Part Number 0130-07977-01P • 4/27/09